



People`s Democratic Republic of Algeria
Ministry of Higher Education and Scientific Research
University of Echahid Hamma Lakhdar - El Oued



Faculty of Technology
Department of Mechanical Engineering Dissertation
ACADEMIC MASTER

Domain: **Science and Technology**
Division: **Mechanical Engineering**
Specialty: **electromechanical**

Presented by:

- 1. SAHRAOUI ABDENNACER**
- 2. AHMIMA ABDELBASSET**
- 3. DRIHEM AYMANE**

Photovoltaic Energy Generation System Based on MPPT Control

Entitled:

Dissertation Submitted in Partial Fulfillment of the Requirements for the Master

MEM

Degree in

Publicly defended in:/..... /2026

Board of Examiners:

Dr.	djokhrab ala eddine	Chairman
Dr.	Largot soulef	Supervisor
Dr.	ben amor afaf	Examiner

Academic Year: 2025-2026

Remerciements

First and foremost, I would like to express my profound gratitude and deepest appreciation to my supervisor,

Dr. Largot Soulef and Dr. BEBOUKHA ALI,

for his exceptional guidance, invaluable mentorship, and continuous support throughout the development of this Master's thesis. His vast expertise, rigorous academic standards, and insightful feedback were the cornerstone of this work. I am truly privileged to have benefited from his wisdom and encouragement.

I would also like to extend my sincere thanks to the distinguished members of the Jury Committee for their time, effort, and scholarly evaluations. Their constructive remarks and dedication to the examination process are highly valued and greatly appreciated.

Special thanks are due to the faculty and staff of the Department of Mechanical Engineering for providing the academic resources and professional environment that made this research possible.

Finally, I wish to express my heartfelt thanks to my Family and Friends for their unconditional support and faith in my potential. Their patience and encouragement have been my greatest strength throughout this journey.

DEDICATION

To the source of my strength and the reason for my perseverance, my beloved Parents, whose prayers and sacrifices paved the way for my success.

To my Sisters and Brothers, for their constant encouragement and for being the light during my darkest hours of study.

To all my Teachers and Mentors, who shared their knowledge and wisdom to shape my intellectual path.

To my Friends and Colleagues, with whom I shared the challenges and triumphs of this academic journey.

Finally, to everyone who believed in me when I doubted myself, and to my homeland, I dedicate this work as a symbol of gratitude and a step toward a brighter future.

Abstract:

This study provides a comprehensive evaluation of Maximum Power Point Tracking (MPPT) techniques for photovoltaic (PV) systems operating under both constant and variable irradiance levels. Through the comparative analysis of Perturb and Observe (P&O), Incremental Conductance (INC), Artificial Neural Networks (ANN), and Fuzzy Logic Controller (FLC), the research documents the specific operational strengths and limitations of each approach. Simulation results within the MATLAB-Simulink environment demonstrate that the ANN algorithm achieves optimal performance in energy extraction, while the FLC effectively minimizes steady-state oscillations through rapid adaptability to environmental shifts. Ultimately, this work underscores the necessity of selecting MPPT methodologies based on specific system requirements and environmental dynamics. Furthermore, it identifies experimental verification and the development of hybrid algorithmic frameworks as critical avenues for future research to enhance overall system performance.

Keywords: MPPT, Photovoltaic Systems, P&O, MATLAB-Simulink, Efficiency, Variable Irradiance, Hybrid Algorithms.

INC: Incremental Conductance

ANN: Artificial Neural Network

FLC: Fuzzy Logic Controller

الملخص

تقدم هذه الدراسة تقييماً شاملاً لتقنيات تتبع نقطة القدرة القصوى (MPPT) لأنظمة الخلايا الكهروضوئية العاملة تحت مستويات إشعاع ثابتة ومتغيرة. ومن خلال التحليل المقارن لتقنيات الاضطراب والملاحظة (P&O)، والتوصيلية التزايدية (INC)، والشبكات العصبية الاصطناعية (ANN)، ووحدة التحكم المنطقية الضبابية (FLC)، توثق الدراسة نقاط القوة والقيود التشغيلية لكل نهج. وتُظهر نتائج المحاكاة في بيئة MATLAB-Simulink أن خوارزمية الشبكات العصبية الاصطناعية تحقق الأداء الأمثل في استخلاص الطاقة، بينما تُقلل وحدة التحكم المنطقية الضبابية بشكل فعال من التذبذبات في الحالة المستقرة من خلال التكيف السريع مع التغيرات البيئية. وفي النهاية، يؤكد هذا العمل على ضرورة اختيار منهجيات تتبع نقطة القدرة القصوى بناءً على متطلبات النظام المحددة وديناميكيات البيئة؛ علاوة على ذلك، يُحدد التحقق التجريبي وتطوير أطر عمل خوارزمية هجينة كسبل حاسمة للبحوث المستقبلية لتحسين أداء النظام بشكل عام.

الكلمات المفتاحية: MPPT، أنظمة الطاقة الكهروضوئية، P&O، INC، ANN، FLC،

Simulink MATLAB-، الكفاءة، الإشعاع المتغير، الخوارزميات الهجينة.

List of Figures

Figure (1.1.1): Global power generating capacity.....	5
Figure (1.1.2): Levelised cost of electricity from newly commissioned solar PV, onshore wind power and offshore wind power, 2010-2021.....	5
Figure (1.1.3): Solar irradiation map of the world from photovoltaic guidenr.	6
Figure (1.1.4): Schematic exhibiting the relationship of a RES to the electricity grid.	7
Figure (1.1.5): A photovoltaic (PV) system with power electronics and the needed control.	8
Figure(2): Classification of DC–DC converters.....	9
Figure (1.1): Representation of Solar Radiation	10
Figure (1.2): Solar Radiation Spectrum	11
Figure (1.3): Representation of Solar Radiation Spectrum	11
Figure (1.4): Solar Radiation Conversion by PV Effect	12
Figure (1.5): Typical Characteristics of a PV Generator.....	13
Figure (1.6): Block Diagram of a PV Generator	14
Figure (1.7): Equivalent Circuit of a PV Cell	15
Figure (1.8): Monocrystalline Cells	16
Figure (1.9): Polycrystalline Cells.....	16
Figure (1.10): Hydrogenated Amorphous Cells	17
Figure (II.1): DC-DC Converters	21
Figure (II.2): Applications of DC/DC Converters.....	22
Figure (II.3): The Circuit Representation of Buck Converter	24
Figure (II.4): Buck Converter When S_1 is Closed	25
Figure (II.5): Buck Converter When S_2 is Closed	26
Figure (II.6): Wave form Representation	28
Figure (II.7): Elementary Circuit of Boost Converter	29
Figure (II.8): The Chopper CH is in on State.....	29
Figure (II.9): The Chopper CH is in Off State	30
Figure (II.10): Waveform Representation	31
Figure (II.11): The Circuit Representation of Buck-Boost Converter	33
Figure (II.12): The Equivalent Circuit of Mode I.....	34
Figure (II.13): The Equivalent Circuit of Mode II	35
Figure (III.1): Block Diagram of The PV System	41
Figure (III.2): Search and Recovery Of MPP.....	41
Figure (III.3): Bloc Diagram of a Digital MPPT Command	45

List of Figures

Figure (III.4): Ppv VS Vpv Characteristic of a Solar Panel	46
Figure (III.5): Divergence of The P & O Command Due to Radiation Variations	47
Figure (III.6): Algorithm of The P & O Type of Command	47
Figure (III.7): State Flowchart of Hill Climbing MPPT Technique	48
Figure (III.8): Flowchart for The Incremental Conductance Algorithm.	49
Figure (III.9): Functioning of Artificial Neural Networks	51
Figure (III.10): Setting Up the Neural Network Fitting Tool	53
Figure (III.11): Neural Network Structure	53
Figure (III.12): Select Data.....	54
Figure (III.13): Import Data.....	54
Figure (III.14): Validation and Test Data	55
Figure (III.15): Network Architecture	55
Figure (III.16): Network Training	56
Figure (III.17): Train Network	56
Figure (IV.1): Characteristics of Panel.....	58
Figure (IV.2): Schema of System Simulation With P&O	59
Figure (IV.3): Duty Cycle Simulation Result	59
Figure (IV.4): Power Simulation Result.....	61
Figure (IV.5): Voltage Simulation Result	62
Figure (IV.6): Current Simulation Result.....	62
Figure (IV.7): Power Simulation Result.....	62
Figure (IV.8): Voltage Simulation Result	63
Figure (IV.9): Current Simulation Result.....	64
Figure (IV.11): Schema of System Simulation With INC	64
Figure (IV.11): Power Simulation Result.....	65
Figure (IV.12): Voltage Simulation Result	66
Figure (IV.13): Current Simulation Result.....	66
Figure (IV.14): Power Simulation Result.....	66
Figure (IV.15): Voltage Simulation Result	66
Figure (IV.16): Current Simulation Result.....	67
Figure (IV.17): Schema of System Simulation With ANN.....	68
Figure (IV.18): Duty Cycle Simulation Result	68
Figure (IV.19): Power Simulation Result.....	68
Figure (IV.20): Voltage Simulation Result	69

List of Figures

Figure (IV.21): Current Simulation Result.....	69
Figure (IV.22): Power Simulation Result.....	70
Figure (IV.23): Voltage Simulation Result	71
Figure (IV.24): Current Simulation Result.....	72
Figure (III.25): Schematic simulation system with FLC	73
Figure (III.26): Power simulation result	73
Figure (III.27): Voltage simulation result.....	74
Figure (III.28): Current simulation result	74
Figure (III.29): Power simulation result	75
Figure (III.30): Voltage simulation result	75
Figure (III.31): Current simulation result.....	76
Figure (IV.25): Current Simulation Result.....	77
Figure (IV.26): Voltage Simulation Result	77
Figure (IV.27): Current Simulation Result.....	76
Figure (IV.28): Voltage Simulation Result	77
Figure (IV.29): Chart of Efficiency	78
Figure (IV.30): Chart of Efficiency	79

List of Tables

List of tables

Table (II.1): Comparison of Converter Types.....	37
Table (II.2): Efficiency of Static Converters.....	37
Table (IV.1): Parameters of Boost Converter.....	58
Table (IV.2): Table of Efficiency.....	78
Table (IV.3): Table of Efficiency.....	79

Summary

Abstract	
List of Figures	
List of tables	
Summary	
General Introduction.....	

Chapter I: Solar Radiation and Photovoltaic Energy

I-1- Introduction	4
I-2- Overview and Motivation	4
I-3- Power Electronics Converters for Renewable Energy System	6
I-3-1- Review of PV Energy System Applications	7
I-3-2- Classification of power converters.....	8
I-3-3- Classification of DC–DC converters	9
I-4- Solar Radiation	10
I-5- Radiation Spectrum	11
I-6- Conversion of Solar Radiation by PV Effect	12
I-7- Photovoltaic Generator.....	12
I-7-1- Photovoltaic Cell.....	14
I-7-2- Modelling of a PV Cell	15
I-8- Types of Photovoltaic Cells	15
I-9- The Impact of Temperature on Solar Panel	17
I-10- Advantages and Disadvantages of PV Energy	18
I-10-1- Advantages.....	18
I-10-2- Disadvantages	18
I-11- Conclusion.....	19

Chapter II: DC-DC Converter

II-1- Introduction.....	21
II-2- DC-DC Converters	21
II-3- Applications of DC-DC Converter	22
II-4- Types of DC-DC converters	24
II-4-1- Buck Converter.....	24
II-4-2- Operating Principle of Buck Converter	24
II-4-3- Boost Converter.....	28
II-5- Operating Principle of Boost Converter	28

Summary

II-6- Buck-Boost Converter	32
II-7- Buck Boost Converter Formula	35
II-8- Comparison of Converter Types	36
II-9- Efficiency of Static Converters	37
II-10- Conclusion	37

Chapter III: Maximum Power Point Tracking

III-1- Introduction	39
III-2- Maximum Power Point Tracking	39
III-3- Working principle of MPPT	40
III-4- Classification of MPPT Control	42
III-4-1- Classification of MPPT Controllers Based on Input Parameters	42
III-4-2- Classification of MPPT Controllers According to the Type of Search.....	43
III-5- Different MPPT Commands Synthesis	44
III-5-1- First MPPT Commands Types	44
III-5-2- Efficient MPPT Commands Algorithms	45
III-5-3- Algorithm Perturb and Observe (P&O)	45
III-5-4- Algorithm Hill Climbing.....	48
III-5-5- Algorithm Incremental conductance (INC)	49
III-5-6- Artificial Neural Networks (ANN)	49
III-6- Application of Artificial Neural Networks in MPPT	51
III-7- Implementation of ANN in MATLAB/SIMULINK	51
III-8- Conclusion.....	56

Chapter IV: Simulation Results

IV-1- Introduction	58
IV-2- Parameters of System Simulation	58
IV-3- Simulation Results.....	59
IV-3-1- P&O Algorithm.....	59
IV-3-2- Incremental Conductance.....	63
IV-3-3- Artificial Neural Network (ANN).....	67
IV-4- Fuzzy Logic Controller (FLC) algorithm.....	71
IV-5- Comparison and Analysis Between (P&O, INC, ANN, FLC).....	75
IV-5-1- Constant Irradiance (1000 W/m^2)	75
IV-5-2- Comparison	75
IV-5-3- Analysis.....	76

Summary

IV-5-4- Variable Irradiances (1000, 900, 700, 1000 W/m ²)	76
IV-5-5- Comparison	77
IV-6- Comparison of efficiency between algorithms (P&O, INC, ANN and FLC)	78
IV-6-1- Constant Irradiance (1000 W/m ²)	78
IV-6-2- Variable Irradiances (1000, 900, 700, 1000 W/m ²)	79
IV-7- Conclusion.....	80
General Conclusion.....	82
Bibliographical references.....	84

General Introduction

The integration of photovoltaic (PV) systems into the global energy matrix has accelerated as the transition toward sustainable and carbon-neutral energy production becomes imperative. The primary advantage of PV technology lies in its ability to convert solar irradiance directly into electricity, thereby mitigating reliance on fossil fuels and reducing environmental degradation. However, the operational efficiency of PV systems remains a significant challenge, as it is highly sensitive to fluctuating atmospheric conditions, specifically solar irradiance and ambient temperature. Under low-light or high-temperature scenarios, the performance of PV arrays can diminish substantially, necessitating advanced optimization strategies to ensure reliable and efficient energy harvesting.

To address these limitations, Maximum Power Point Tracking (MPPT) techniques have become an indispensable component of modern PV architectures. These algorithms dynamically adjust the system's operating point to ensure maximum power extraction despite environmental variability. The primary objective of this thesis is to provide a rigorous comparative assessment of four prominent MPPT methodologies: Perturb and Observe (P&O), Incremental Conductance (INC), Artificial Neural Networks (ANN), and Fuzzy Logic Control (FLC). Through comprehensive simulations, this research evaluates each algorithm's transient response, steady-state stability, and adaptability to dynamic irradiance profiles. The findings demonstrate that while conventional methods like P&O offer implementation simplicity, intelligent approaches such as ANN provide superior performance and robustness in volatile conditions.

To provide a systematic presentation of this research, the thesis is structured into four primary chapters.

Chapter I: Solar Radiation and Photovoltaic Energy.

Chapter II: DC-DC Converter.

Chapter III: Maximum Power Point Tracking.

Chapter IV: Simulation Results.

Through this comparative study, we aim to provide a comprehensive framework for selecting the most effective MPPT techniques to maximize the efficiency of photovoltaic systems. While the results identify the ANN-based approach as the superior solution across most operating scenarios, the analysis also underscores the functional relevance of FLC and INC depending on specific system constraints and implementation requirements. Ultimately, this research contributes to the ongoing advancement of solar energy technologies, offering insights that facilitate the development of more efficient, robust, and reliable renewable energy infrastructures for the future.

Chapter I
Solar Radiation and
Photovoltaic Energy

I-1- Introduction :

Solar radiation, being the largest energy resource available on earth, represents the main energy supply of photovoltaic (PV) systems, Photovoltaic energy (or solar) is produced using photovoltaic cells that convert sunlight into electricity.

In this chapter, general information on solar energy will be described, We will outline the principles of photovoltaic systems and electricity production from sunlight based on the photovoltaic effect, We'll talk about the differences in solar energy by location and season.

I-2- Overview and Motivation:

The escalating global demand for electrical energy, predominantly met by fossil fuel combustion, has placed unprecedented pressure on finite reserves while significantly degrading the global environment. The continued reliance on coal and oil results in substantial greenhouse gas emissions specifically carbon dioxide (CO₂), methane (CH₄), and nitrous oxide (N₂O) which serve as primary catalysts for climate change (IPCC, 2007). Furthermore, the intensive use of these fuels in transportation and expanding industrial sectors has induced severe air pollution, necessitating a global transition toward sustainable and clean energy alternatives to safeguard natural ecosystems [1, 2], As emphasized by international frameworks such as the Kyoto Protocol, achieving long-term economic growth requires coordinated efforts to mitigate these environmental impacts [3].

In response to these challenges, renewable energy sources (RES) have emerged as the fundamental alternative for modern power generation, Over the past few decades, the integration of RES into electricity grids has grown substantially, driven by strategic policy measures aimed at ensuring energy security and climate stability (World Energy Outlook), By 2023, renewable sources accounted for over 33% of the global power generation capacity, reflecting their critical role in the contemporary energy mix [4], Unlike conventional fuels, solar, wind, biomass, and hydroelectric power facilitate carbon-free energy production, offering a viable pathway to mitigate global warming and drastically reduce atmospheric pollution.




Figure (1.1.1): Global power generating capacity [4].

Among renewable energy technologies, solar photovoltaic (PV) and wind power have demonstrated the most substantial growth, significantly outpacing other forms of sustainable energy. As illustrated in Figure 1.2, PV systems and wind power constitute approximately 33% and 28% of new renewable energy installations, respectively, underscoring their pivotal role in the global transition toward decarbonizing the energy sector. However, the geographical potential for solar energy harvesting varies considerably by region, as depicted in the global solar resource map in Figure 1.3, which necessitates the implementation of optimized system designs to account for regional irradiance fluctuation.




Figure (1.1.2): Levelised cost of electricity from newly commissioned solar PV, onshore wind power and offshore wind power, 2010-2021 [5].




Figure (1.1.3): Solar irradiation map of the world from photovoltaic guidenr.

The Levelized Cost of Electricity (LCOE) for renewable technologies has witnessed a substantial decline; notably, onshore wind energy saw a 50% reduction between 2010 and 2022, reaching USD 0.033/kWh, Solar photovoltaic (PV) systems followed a similar trend with a recorded LCOE of USD 0.049/kWh, while offshore wind remains higher at USD 0.081/kWh (Figure 1.2), Despite this improved cost-efficiency, the intermittent nature of solar PV poses significant grid integration challenges, The inherent variability of the direct current (DC) output, driven by fluctuating environmental conditions, renders direct connection to the electrical grid impractical.

To address these instabilities, Power Electronic Converters (PECs) have emerged as a pivotal technological solution, Acting as intermediary devices, PECs dynamically regulate the fluctuating output voltage to ensure efficient power conversion and balanced distribution, By providing these critical regulatory functions, PECs enhance grid compatibility and guarantee the reliable delivery of power generated from renewable sources.

I-3- Power Electronics Converters for Renewable Energy System:

Power Electronic Converters (PECs) play an indispensable role in facilitating the seamless integration of renewable energy sources (RES) with electrical grids and load systems, Their operation is a critical determinant of overall system performance, directly influencing stability, reliability, efficiency, power quality, and the energy consumption ratio, To achieve cost effective and efficient energy conversion, innovative converter architectures are being developed in parallel with the expanding deployment of renewable technologies [4].

As illustrated in Figure 1.4, the incorporation of RES into electrical infrastructures necessitates the use of PECs to synchronize intermittent outputs with stringent grid requirements. Consequently, research focus has shifted toward enhancing PEC efficiency through two primary technological avenues: (a) the engineering of novel power converter topologies and (b) the implementation of advanced control strategies.




Figure (1.1.4): Schematic exhibiting the relationship of a RES to the electricity grid.

The classification of power converters within renewable energy systems (RES) is broadly divided into two primary categories: galvanically isolated and non-isolated topologies [6, 7]. Galvanically isolated converters, frequently referred to as transformer-based systems, utilize a transformer to provide electrical isolation between the input and output stages [8, 9, 10]. While this isolation mechanism enhances safety and functional versatility, the integration of transformers introduces significant drawbacks, including increased capital costs, greater physical volume, and inherent efficiency losses. Conversely, non-isolated or transformer less solutions bypass these limitations, as substantiated by empirical case studies [11, 12]. Consequently, when evaluating cost effectiveness, compact design, and operational efficiency, non-isolated converters emerge as the superior choice for modern power conversion processes.

I-3-1- Review of PV Energy System Applications:

Photovoltaic (PV) energy conversion systems are fundamental to the integration of renewable sources into the utility grid, offering a sustainable framework for efficient electricity generation. As illustrated in the structural configuration in Figure 1.5, the process initiates with PV arrays that harvest solar irradiance to generate direct current (DC) power,

which is subsequently stabilized through DC bus architectures, The pivotal stage involves a multilevel power electronics converter, which facilitates the conversion of DC power into high-quality alternating current (AC) while minimizing Total Harmonic Distortion (THD), This is followed by a filtering stage designed to attenuate high-frequency noise and ensure compliance with stringent grid standards, with an optional transformer incorporated for voltage adaptation and galvanic isolation, Central to this architecture is the control unit, which integrates a Maximum Power Point Tracking (MPPT) controller to optimize energy extraction and precisely regulate the power electronic interface, This sophisticated synergy of advanced control algorithms and conversion technologies ensures both efficient solar energy utilization and seamless grid compatibility.




Figure (1.1.5): A photovoltaic (PV) system with power electronics and the needed control.

I-3-2- Classification of power converters:

Power electronic converters have been used in many industrial applications for efficient power conversion and energy conservation, Depending on the type of electric power conversion and the electric power flow, the power converters can be divided into the following four categories:


- AC-DC rectifiers: Convert a single-phase or three-phase AC voltage to DC is used as front-end in variable-speed motor drives and wind energy conversion systems.
- DC-DC converters: Convert a DC voltage from one level and a certain polarity to a DC voltage of another level and in some applications to another polarity.
- DC-AC inverters: Conversion from DC to variable-voltage and variable-frequency AC is used invariable-speed motor drives. Conversion of unregulated or regulated DC to fixed AC is used in grid-connection of renewable energy sources.

- AC-AC cycloconverters: Convert an AC voltage of one level, frequency and number of phases to an AC voltage of a different level, frequency, and in some applications to different number of phases.

I-3-3- Classification of DC–DC converters:

Extensive research has been conducted on various DC–DC converter topologies for renewable energy and storage applications, focusing on enhancing efficiency and mitigating inherent operational weaknesses, As illustrated in Figure 2, these converters are categorized into three primary technologies based on their switching modes: linear, hard-switching, and soft switching [13-15], The linear mode is characterized by structural simplicity, low noise, and rapid response; however, it suffers from low efficiency due to significant power losses across diverse operating conditions.

Hard-switching converters are further classified into non-isolated and isolated variants, Non-isolated topologies, such as Buck, Boost, Buck Boost, and Cuk converters, are identified as chopper circuits. In contrast, galvanically isolated converters utilize transformers to ensure safety when interfaced with the utility grid, While power electronic converters and their associated control strategies are essential for regulating node voltages within microgrids supporting resistive, inductive, and non-linear loads the presence of Constant Power Loads (CPLs) poses a significant challenge, CPLs inherently destabilize output voltage and are notoriously difficult to regulate using traditional control techniques [16, 17].



Figure(2): Classification of DC–DC converters [18].

I-4- Solar Radiation :

Solar radiation encompasses the entire spectrum of energy emitted by the Sun, Beyond cosmic rays, those high-velocity, high-energy particles that traverse the vacuum of space the Sun radiates a diverse array of electromagnetic waves, These span from the broad reaches of radio waves to the high-frequency intensity of gamma rays, fundamentally including the visible light that defines our perception of the world.

The Sun's electromagnetic emission is precisely modeled as a black body at 5800 Kelvin, governed by Planck's Law, This physical model reveals an emission peak within the yellow spectrum ($\lambda = 570 \text{ nm}$), The total energy is distributed almost equally between visible light and infrared radiation, with a critical 1% residing in the ultraviolet range, However, before reaching sea level, this radiation must undertake a vital journey through the Earth's atmosphere, This transition is not merely a physical passage but a sophisticated process of "natural filtration," The atmosphere acts as a protective cradle, where absorption bands of ozone, oxygen, carbon dioxide, and water vapor selectively intercept harmful solar components [1].



Figure (1.1): Representation of Solar Radiation

I-5- Radiation Spectrum:

While solar energy is often theorized as an abstract physical construct, it is fundamentally rooted in the primordial human experience of the Sun's thermal and luminous radiation. The advent of photovoltaic technology in the last century catalyzed a profound shift in this relationship, evolving our role from passive observers of sunlight to active architects of its power. By leveraging the photovoltaic effect, we can now directly transduce the latent energy of photons into a regulated electrical flow.




Figure (1.2): Solar Radiation Spectrum

The electromagnetic spectrum encompasses a vast range of wavelengths; however, approximately 99.8% of solar radiant energy is concentrated within a narrow bandwidth ranging from 20 to 2500 nanometers.

As this radiation propagates through the terrestrial environment, the atmosphere and ionosphere function as selective filters, reflecting or absorbing a significant portion of the energy. Consequently, only a specific spectral fraction reaches the Earth's surface, extending from decametric radio waves to attenuated ultraviolet radiation [2].

As depicted in Figure (1.3), the terrestrial solar spectrum is comprised of approximately 5% ultraviolet radiation, 42% visible light, and 53% near infra-red radiation.




Figure (1.3): Representation of Solar Radiation Spectrum

I-6- Conversion of Solar Radiation by PV Effect:

The fundamental unit of this technology is the photovoltaic cell, a semiconductor device consisting of two distinct silicon layers specifically doped to establish polarization. The introduction of boron atoms creates a positive ("P-type") layer, while phosphorus atoms characterize the negative ("N-type") layer, thereby forming a permanent potential barrier. The photovoltaic effect occurs when the semiconductor absorbs a photon possessing energy greater than the material's bandgap, causing the rupture of a valence bond and the subsequent liberation of an electron, creating a positive "hole". This is what is called the photovoltaic effect: The resulting potential difference between the layers drives an orderly migration of electrons when an external circuit is connected, effectively converting electromagnetic energy into a continuous electric current [1].




Figure (1.4): Solar Radiation Conversion by PV Effect

I-7- Photovoltaic Generator:

The performance of a photovoltaic (PV) sensor is defined by its characteristic electrical properties, specifically the non-linear relationship between current and voltage ($I=f(V)$), as depicted in Figure (1.5).

This mathematical modeling is utilized to determine the electrical output based on two primary environmental variables: incident irradiance and cell temperature received by the sensor.

The current generated by a photovoltaic module at a specific voltage is a direct function of the incident irradiance and the cell temperature. Under constant environmental conditions, the conversion efficiency is governed by the impedance of the external electrical circuit. In an open-circuit state ($R_c = \infty$, $I = 0$, $V = V_{oc}$) or a short circuit state ($R_c = 0$, $I = I_{cc}$, $V = 0$), the

power transfer to the external load is zero. Between these operational boundaries, an optimal load resistance (R_{opt}) exists, at which the power delivered by the photovoltaic cell reaches its maximum value (P_{max})

($P = V_{max} \times I_{max}$) provided by the solar cell to the load resistance is maximal, thus reaching P_{max} [2].




Figure (1.5): Typical Characteristics of a PV Generator

The energy conversion efficiency of a solar cell, denoted as η , is defined by the ratio: $\eta = P_{max}/P_{\gamma}$, where P_{γ} represents the incident solar power projected onto the cell's surface. At the optimal load resistance (R_{opt}), the device operates at its peak efficiency such that $\eta = \eta_{max}$. It is important to note that R_{opt} is not an intrinsic constant of the cell; rather, it is dynamically dependent on the incident spectral distribution and the junction temperature.

In practice, photovoltaic efficiency exhibits an inverse relationship with temperature, where increased thermal energy leads to a decrease in the semiconductor's performance. To mitigate this thermal degradation, hybrid photovoltaic-thermal (PVT) systems are often employed. These integrated sensors facilitate the simultaneous generation of thermal energy (e.g., hot water) while enhancing electrical efficiency by actively cooling the photovoltaic cells, thereby maintaining the operating temperature within an optimal range.

The electrical power output of a photovoltaic cell, defined by the relation $P = I \times V$, and its conversion efficiency are multifaceted functions of intrinsic and extrinsic determinants. Intrinsically, these metrics are governed by the material properties and fabrication technologies specifically the distinction between amorphous, polycrystalline, and monocrystalline silicon as well as the architectural geometry of the junction, including layer thickness and multi junction configurations. Extrinsically, performance is modulated by environmental and operational parameters, notably the operating temperature, the spectral

composition and intensity of incident irradiance, and the impedance characteristics of the interfaced external electrical circuit.




Figure (1.6): Block Diagram of a PV Generator

I-7-1- Photovoltaic Cell:

Photovoltaic modules are composed of a systematic arrangement of interconnected solar cells, encapsulated within a resin medium and protected between two layers of tempered glass (double-glass modules) or a combination of a frontal glass pane and a Tedlar sheet (glass/Tedlar module). This assembly is typically integrated into an anodized aluminium frame to ensure mechanical stability; however, frameless modules are also employed in building integration applications, utilizing aluminium profiles for mounting on facades or roofs. The power generated by a module is determined by its surface area and the level of incident solar irradiation, quantified in peak watts (W_p). This unit represents the maximum power output of the module under a reference solar irradiation of (1000 W/m^2).

The terminal voltage of a photovoltaic module is fundamentally determined by the number of cells configured in series. For low capacity modules ($< 75 \text{ W}_p$), the nominal operating voltage typically ranges between 12 and 15 V. Higher power ratings are achieved through a combination of series and parallel configurations: increasing the number of series connected cells scales the output voltage, while the integration of parallel branches enhances the total current capacity. Consequently, operating voltages of 24 V or higher are common, depending on the specific load requirements of the system architecture.

While module surface area varies by manufacturer generally ranging from 0.5 to 1 square meter specialized large scale productions may reach dimensions of up to 3 square meter . In terms of hierarchical assembly, multiple interconnected modules constitute a panel, while the collective interconnection of panels forms a photovoltaic array. This modular scalability allows for the precise tailoring of voltage and power output to meet diverse energy demands[1].

I-7-2- Modelling of a PV Cell:

The operational behavior of a photovoltaic module is fundamentally characterized by the standard single diode model, originally established by Shockley for individual cells and subsequently generalized for modules by treating them as an assembly of identical cells in series and parallel configurations.

In technical literature, a photovoltaic cell is modeled as an electrical current generator, whose equivalent circuit consists of a constant current source in parallel with a rectifying diode. To accurately simulate the physical loss mechanisms inherent in the semiconductor, this ideal model is augmented by two parasitic resistances: the series resistance (R_s) and the shunt (parallel) resistance (R_{sh}), as illustrated in the equivalent circuit diagram in Figure (1.7).

The series resistance accounts for the ohmic losses within the device, primarily determined by the bulk resistance of the semiconductor material, the contact resistance between the metal grids and the semiconductor, and the intrinsic resistivity of the collection grids. Conversely, the shunt resistance represents the leakage current across the p-n junction, typically resulting from structural defects or impurities introduced during the fabrication process.




Figure (1.7): Equivalent Circuit of a PV Cell

I-8- Types of Photovoltaic Cells :

Photovoltaic solar panels are made up of photovoltaic cells and vary according to type:

1. Monocrystalline Silicon Cells: These cells are fabricated from a single, continuous crystal lattice structure, typically produced through the controlled cooling and solidification of molten silicon. This process results in a high-purity, uniform crystalline matrix, which is subsequently precision sliced into thin wafers. Characterized by a deep, consistent blue aesthetic, this material is distinguished by its structural homogeneity, appearing devoid of visible crystal boundaries or macroscopic impurities.



Figure (1.8): Monocrystalline Cells

2. Polycrystalline Silicon Cells: The production of polycrystalline silicon involves the melting of silicon within specialized elongated rectangular molds, referred to as ingots. Unlike the single crystal variety, this cooling process allows for the formation of multiple distinct crystalline grains. Visually, these cells exhibit a variegated blue hue with a characteristic speckled appearance, reflecting the randomized orientation of the internal crystal fragments. This multi grain morphology serves as a primary diagnostic feature for the identification of this specific cell category.



Figure (1.9): Polycrystalline Cells

3. Hydrogenated Amorphous Silicon Cells: This technology utilizes silicon in a gaseous state, which is deposited onto a substrate such as glass, flexible polymers, or metallic surfaces via a vacuum based vaporization and deposition technique. This process creates a

non crystalline, disordered atomic structure rather than a rigid lattice, These cells are physically characterized by a dark gray tonality and a thin film profile, differing significantly from the traditional wafer based silicon technologies.



Figure (1.10): Hydrogenated Amorphous Cells

I-9- The Impact of Temperature on Solar Panel:

Thermal influence constitutes a critical factor in the operational performance of photovoltaic modules, characterized by several key degradation mechanisms:

- **Efficiency Attenuation:** An inverse correlation exists between operating temperature and conversion efficiency, Elevated thermal states increase internal carrier recombination rates, thereby reducing the efficiency of photon to electron conversion.
- **Voltage Reduction:** The open circuit voltage (V_{oc}) exhibits a negative temperature coefficient, As the semiconductor temperature rises, the bandgap narrows, leading to a decrease in the potential barrier and a subsequent decline in terminal voltage.
- **Power Output Diminution:** The aggregate power output (P_{max}) is compromised by the concurrent reduction in voltage and conversion efficiency. This thermal sensitivity necessitates the use of temperature coefficients to calculate real world yield.
- **Thermal Degradation:** Sustained exposure to elevated temperatures induces mechanical and chemical stresses on the encapsulation materials and semiconductor junctions, potentially accelerating aging and reducing the device's operational lifespan.
- **Operating Thresholds:** PV modules are engineered for specific thermal ranges, Operation beyond these design limits can induce non linear performance losses and permanent structural compromise.

In summary, while photovoltaic generation remains active under high irradiance, the concomitant rise in cell temperature acts as a limiting factor, necessitating thermal management strategies to optimize overall system output.

I-10- Advantages and Disadvantages of PV Energy:

I-10-1- Advantages:

- **Renewable Resource Abundance:** Solar irradiance represents a ubiquitous and inexhaustible energy flux, providing a viable foundation for long term energy sustainability on a global scale.
- **Decarbonization and Emission Mitigation:** Photovoltaic conversion is characterized by the absence of atmospheric pollutants and greenhouse gas emissions during operation, contributing significantly to the reduction of carbon footprints and the mitigation of anthropogenic climate change.
- **Technoeconomic Viability:** Substantial reductions in the levelized cost of energy for solar technologies have enhanced their competitiveness relative to fossil fuel based power generation.
- **Energy Decentralization and Security:** Distributed photovoltaic generation facilitates energy autonomy, mitigating reliance on centralized utility grids and shielding consumers from the volatility of energy market pricing.
- **Operational Reliability:** Photovoltaic installations are characterized by a lack of moving parts, resulting in minimal maintenance requirements and high operational reliability over the system's lifecycle.

I-10-2- Disadvantages:

- **Intermittency and Temporal Variability:** Photovoltaic generation is inherently non continuous, dictated by diurnal cycles and atmospheric conditions, This stochastic nature necessitates the implementation of energy storage systems or hybridization with complementary power sources to ensure grid stability and supply demand synchronization.
- **Capital Intensity:** Although levelized costs have declined, the acquisition and installation of photovoltaic infrastructure require substantial upfront capital expenditure, These initial investment requirements remain a significant barrier to entry compared to traditional decentralized energy solutions.
- **Life Cycle Environmental Considerations:** While operationally carbon neutral, the life cycle of photovoltaic modules involves energy intensive manufacturing processes and the utilization of specific chemical precursors. Furthermore, the absence of standardized, large scale end of life management and recycling protocols poses long term waste management challenges.

- **Spatial Density Requirements:** Due to the relatively low energy density of solar radiation, significant surface area either terrestrial or structural is required to achieve high power capacities, This spatial demand introduces land use competition and complicates deployment in high density urban environments.
- **Meteorological Sensitivity:** System efficiency is highly susceptible to transient meteorological phenomena, such as cloud cover, precipitation, and particulate accumulation (soiling), These factors induce power fluctuations and reduce predictable energy yield.

I-11- Conclusion:

In conclusion, this chapter analyzed the fundamental principles of solar irradiance and the mechanisms of photovoltaic energy conversion, It detailed the semiconductor physics of the photovoltaic effect and characterized the electrical behavior of generators through single diode modeling, emphasizing the influence of temperature and impedance matching on efficiency, Furthermore, the structural classification of silicon based cells was examined alongside module architecture. Finally, a technical assessment of the operational advantages and systemic constraints of photovoltaic technology provided a comprehensive framework for the subsequent study.

Chapter II

DC-DC Converter

II-1- Introduction :

DC-DC converters represent fundamental electronic architectures that serve as the backbone of modern power management systems. Their core utility lies in the efficient transformation of direct current (DC) voltage from one magnitude to another, a process that ensures consistent and optimized energy delivery across diverse electronic frameworks. In environments where input sources are inherently unstable such as the gradual depletion of a battery or shifting load demands these converters act as a critical stabilization layer, maintaining a fixed output voltage to guarantee the reliability of downstream components. A primary advantage of these systems is their exceptional conversion efficiency, achieved through high-frequency switching techniques. By modulating energy flow in discrete intervals, they significantly mitigate the thermal losses typically associated with resistive elements found in linear regulators, thereby preserving energy and extending the operational lifespan of portable electronics. Beyond simple voltage regulation, DC-DC converters provide the architectural flexibility to either step up or step down voltage levels, facilitating sophisticated power distribution. Furthermore, many designs incorporate galvanic isolation, which electrically separates input and output stages to eliminate ground loops and shield sensitive semiconductor devices from transient voltage spikes and noise.

II-2- DC-DC Converters:

DC-DC converters are specialized static power electronics designed to interface with a direct current source to produce a precisely adjustable output voltage across a designated load. To accommodate varying industrial demands, these converters are engineered using different semiconductor technologies tailored to specific power scales. For high capacity applications reaching several hundred megawatts, converters are typically constructed using thyristors, which operate at a chopping frequency in the kilohertz range.

Conversely, for lower power requirements generally ranging up to 100 kW the architecture utilizes transistors. These components allow for significantly higher chopping frequencies, reaching up to 100 kHz.

The following figure illustrates the symbol of a DC-DC converter.




Figure (II.1): DC-DC Converters

II-3- Applications of DC-DC Converter:

For several years, switch mode power converters have permeated contemporary electronics across the industrial, commercial, utility, and consumer sectors, In the realm of low-power DC-DC conversion, the architectural landscape is dominated by three fundamental topologies: the buck, boost, and buck-boost converters, However, as system requirements become increasingly specialized, advanced configurations or modified variations of these conventional designs are necessitated to meet specific performance benchmarks, The lack of a "universal" converter in the literature underscores the diversity of the field, where conversion techniques are tailored to a wide array of applications spanning rigorous industrial research to daily consumer electronics [4].

DC-DC converters represent a cornerstone of power electronics and energy drives, serving as integral components in a multitude of industrial frameworks, as illustrated in **Figure (II.2)**. High voltage gain converters, in particular, are deployed in sophisticated environments such as radar systems, data centers, and the integration of renewable energy sources [5], This capability is especially vital for renewable applications, where high gain converters facilitate the significant voltage step-up required for seamless distribution system integration, Overall, the transition toward DC distribution offers compelling advantages including a reduction in total conversion stages, lower systemic costs, and superior power quality establishing it as the preferred infrastructure for modern energy management.




Figure (II.2): Applications of DC/DC Converters.

Here are some of DC-DC converter applications:

- **Renewable Energy Applications:** DC-DC converter topologies utilized in renewable energy systems are specifically engineered to draw a continuous and smooth input current,

a critical requirement for achieving significant ripple reduction, This steady current profile is essential for protecting the longevity of sources like photovoltaic panels and fuel cells, Furthermore, these converters must demonstrate the versatility to integrate seamlessly with diverse power sources within a unified system, To meet these demands, non isolated interleaved high voltage gain configurations are typically the preferred choice for interfacing renewables with microgrids, as they provide the necessary voltage boost while distributing current across multiple paths to enhance reliability and efficiency [6].

- **Medical devices:** Isolated DC-DC converters are indispensable in medical environments where patient and operator safety is the paramount concern, Their primary function is to provide a robust galvanic barrier, effectively separating the output stage from potentially hazardous voltages on the input side to prevent electrical shock. In contrast, non isolated converter topologies may be utilized for specific high power medical applications, such as the power supply units for X-ray systems, where the engineering focus shifts toward managing extreme voltage levels and rapid energy discharge while maintaining system level insulation.
- **Vehicles:** In the automotive sector, the primary DC-DC converter serves as a critical power distribution hub, stepping down the high voltage energy from the onboard traction battery to the lower DC levels required to operate essential auxiliary systems such as lighting, wipers, and window controls [7]. This architectural requirement is universal across both fully electric (EV) and hybrid electric vehicles (HEV), Within these systems, galvanic isolation is a mandatory safety and functional feature, ensuring that sensitive low voltage control circuits are strictly decoupled from the high voltage propulsion domain, Furthermore, specialized topologies are employed to meet specific voltage needs: buck boost converters provide the versatility to either step up or step down voltage as load conditions fluctuate, while charge pump converters are frequently integrated for efficient voltage inversion.
- **Smart lighting:** In modern lighting technology, LED backlight driver solutions must satisfy a rigorous set of performance criteria, including high conversion efficiency, precise direct current regulation, and integrated overvoltage protection, Furthermore, these systems frequently necessitate PWM based control for flicker free dimming and a streamlined design to minimize manufacturing complexity, Several DC-DC converter architectures serve as effective drivers for these applications: linear regulators are often chosen for their simplicity and low noise in very low-power scenarios, while charge pumps provide a compact, inductor less solution for moderate voltage boosting, For more

demanding configurations, conventional switching converters remain the standard choice, offering the high power density and efficiency required to drive sophisticated LED arrays across consumer and industrial displays.

II-4- Types of DC-DC converters:

There are three types of DC-DC converters, namely: Buck, Boost, and Buck-Boost.

II-4-1- Buck Converter:

The Buck Converter is a fundamental class of DC-DC converter specifically engineered to perform step down conversion of an applied DC input signal, Its primary function is to transform a fixed DC input into a regulated output signal of a significantly lower magnitude, By precisely modulating the energy flow, the buck converter ensures that the output voltage consistently maintains a value below that of the source, effectively "bucking" the voltage down to the required level, Due to this characteristic behaviour, it is frequently referred to in technical literature as a Step down DC-DC Converter, a Step down Chopper, or a Buck Regulator.

II-4-2- Operating Principle of Buck Converter




Figure (II.3): The Circuit Representation of Buck Converter

The architectural layout of the Buck converter highlights the strategic integration of a primary solid state switching device such as a power MOSFET coordinated with a secondary switch in the form of a freewheeling diode, This dual switch configuration is coupled with a low pass LC filter to effectively suppress high-frequency noise and minimize voltage and current ripples, thereby ensuring a stable, regulated DC output, To complete the circuit, a pure resistive element is connected across the output to serve as the system load.

The operational cycle of this converter is divided into two distinct intervals, the first of which occurs when the power MOSFET (Switch S_1) is closed, During this conduction phase, the switch enters an "ON" state, creating a direct path that allows current to flow from the DC

source into the circuit, As current passes through the inductor, energy is stored in its magnetic field while simultaneously powering the load, marking the beginning of the energy transfer process that characterizes step down regulation.




Figure (II.4): Buck Converter When S_1 is Closed

Upon the application of a fixed DC voltage to the input terminals, the closure of switch S_1 initiates a specific current path through the network, During this conduction interval, the inductor positioned directly in the current's trajectory begins to store energy within its magnetic field as the current ramps upward, Simultaneously, the capacitor receives a portion of this energy, accumulating charge and smoothing the voltage transitions to ensure a steady potential is maintained, Consequently, the energy stored and filtered by these reactive components manifests as a regulated output voltage across the resistive load, establishing the initial phase of the step-down conversion process.

However, due to Lenz's law, the energy stored within the inductor will oppose the cause which has produced it and so an induced current will get generated and the polarity across the inductor will get reversed.

Here the total time period is a combination of T_{on} and T_{off} time.

$$T = T_{on} + T_{off} \quad (II. 1)$$

The duty cycle is written as:

$$D = \frac{T_{on}}{T} \quad (II. 2)$$

On applying KVL, in the above-given circuit

$$V_s = V_L + V_{out} \quad (II. 3)$$

$$V_L = V_s - V_{out} \quad (II. 4)$$

Also,

$$V_L = L \frac{di_L}{dt} = V_s - V_{out} \quad (II. 5)$$

$$\frac{di_L}{dt} = \frac{V_s - V_{out}}{L} \quad (II. 6)$$

When S1 is in closed condition then $T_{on} = DT$ thus $\Delta t = DT$. Therefore, we can write

$$\frac{\Delta i_L}{\Delta t} = \frac{V_s - V_{out}}{L} \quad (II. 7)$$

$$\frac{\Delta i_L}{DT} = \frac{V_s - V_{out}}{L} \quad (II. 8)$$

Hence,

$$\Delta i_t = \left(\frac{V_s - V_{out}}{L} \right) DT \quad (II. 9)$$

The above equation represents the change in current through the circuit when switch S1 is closed.

Now, the second mode of operation takes place when switch S₂ is closed and S₁ gets open, However, you must be thinking about how automatically, the switch S₂ will be closed. So, as we have discussed that the inductor in the circuit will store the energy so, once S₁ will get open the inductor in the circuit will start acting as the source, In this mode, the inductor releases the energy which is stored in the previous mode of operation, As we have discussed that the polarity of the inductor will get reversed therefore this causes the freewheeling diode to come in a forward biased state which was earlier present in a reverse biased state due to the applied dc input.

Due to this, the flow of current takes place in a way as shown below:




Figure (II.5): Buck Converter When S₂ is Closed

This flow of current will take place till the time the stored energy within the inductor gets completely collapsed, As once the inductor gets completely discharged, the diode comes

in reverse biased condition leading to cause opening of switch S_2 , and instantly switch S_1 will get closed and the cycle continues.

Now, let us apply KVL, in the above circuit

$$0 = V_L + V_{out} \quad (II. 10)$$

$$V_L = L \frac{di_L}{dt} = -V_{out} \quad (II. 11)$$

Since, we know,

$$T = T_{on} + T_{off} \quad (II. 12)$$

$$T = DT + T_{off} \quad (II. 13)$$

$$T_{off} = T - DT \quad (II. 14)$$

$$T_{off} = (1 - D)T \quad (II. 15)$$

$$V_L = L \frac{\Delta i_L}{\Delta t} = -V_{out} \quad (II. 16)$$

$$T_{off} = \Delta t = (1 - D)T \quad (II. 17)$$

$$L \frac{\Delta i_L}{(1 - D)T} = -V_{out} \quad (II. 18)$$

So,

$$\Delta i_L = -\frac{V_{out}}{L}(1 - D)T \quad (II. 19)$$

This equation represents the rate of change in current through the inductor when the switch S_1 is open.

As we know that the net change of current through the inductor in one complete cycle is zero. Thus,

$$\Delta i_{L(S1-closed)} + \Delta i_{L(S1-open)} = 0 \quad (II. 20)$$

$$\frac{V_s - V_{out}}{L}DT + \left\{ -\frac{V_{out}}{L}(1 - D)T \right\} = 0 \quad (II. 21)$$

On simplifying,

$$\frac{V_s DT}{L} - \frac{V_{out} DT}{L} - \frac{V_{out} T}{L} + \frac{V_{out} DT}{L} = 0 \quad (II. 22)$$

$$\left(\frac{V_s DT}{L} \right) = \frac{V_{out} T}{L} \quad (II. 23)$$

$$V_{out} = DV_s \quad (II. 24)$$

The figure given below represents the waveform representation of Buck Converter:




Figure (II.6): Wave form Representation

Hence, we can say, buck converters are used to provide a lower value of dc signal from a fixed dc input.

II-4-3- Boost Converter:

The Boost Converter, also widely recognized as a step-up DC-DC converter, is a specialized class of chopper circuit engineered to produce an output voltage significantly higher than the initial supply voltage. The fundamental principle of its operation lies in its ability to "boost" the magnitude of the DC signal, transforming a low voltage input into a high magnitude output suitable for more demanding loads. This characteristic makes it the inverse of a buck converter, as it focuses on maximizing the potential energy delivered to the system. The designation "boost" serves as a literal description of its primary function: elevating the electrical potential to a level that exceeds the source input.

II-5- Operating Principle of Boost Converter

The figure given below is the circuit representation of the boost converter:




Figure (II.7): Elementary Circuit of Boost Converter

The fundamental architecture of this step-up DC-DC converter is characterized by the strategic placement of a large inductor (L) in series with the input voltage source. This configuration is essential for the circuit's primary objective: maintaining a stable, regulated DC output at a higher potential than the input. To achieve this, the system relies on the energy storage properties of the inductor, which acts as a bridge between the supply and the load.

The operational cycle begins when the chopper (CH), acting as the primary switch, enters the "ON" state. During this interval, the closed switch creates a low resistance path, causing current to ramp up as it flows from the DC source directly through the inductor. As the current circulates through this internal loop, the inductor absorbs energy from the source and stores it within its magnetic field. During this specific phase, the load is typically isolated from the source by a diode, and the inductor prepares to "boost" the voltage in the subsequent phase of operation.




Figure (II.8): The Chopper CH is in on State

During this conduction interval, the inductor's polarity is established relative to the direction of current flow, with energy accumulating as the magnetic field expands. In this specific configuration, the output diode is maintained in a reverse biased state, effectively

isolating the load from the input source while the switch remains closed. Consequently, no current passes through the output branch during the "ON" state of the converter.




Figure (II.9): The Chopper CH is in Off State

At the instant the chopper (CH) transitions to the "OFF" state, the primary conduction path is interrupted, rendering the previous internal loop inactive. However, due to the energy stored within the inductor's magnetic field, the current cannot cease instantaneously. In accordance with Lenz's Law, the inductor generates an induced electromotive force (EMF) to oppose the sudden decrease in current, causing the inductor's polarity to reverse relative to its charging state.

This reversal in polarity places the inductor in series with the input source, effectively "stacking" their voltages. This combined potential shifts the diode into a forward biased state, creating a path for the stored energy to be delivered to the load. During this interval (T_{off}), the inductor acts as a secondary source, discharging its energy into the system. It is important to note that during this phase, the inductor current is of a decreasing nature, gradually depleting until the next switching cycle begins or the field completely collapses.

Thus, the total voltage across the load will be given as:

$$V_{out} = V_{in} + V_L \quad (II. 25)$$

This means that the output voltage exceeds the applied input voltage. Thus, it performs step up conversion as the energy stored within the inductor during the T_{on} period is released during the T_{off} period.

During the T_{on} period, the voltage across the inductor will be given as:

$$V_L = L \frac{di}{dt} \quad (II. 26)$$

Let us have a look at the waveform representation of the step-up chopper shown below:




Figure (II.10): Waveform Representation

During the T_{on} period, the current through the inductor will change from i_1 to i_2 this is clearly shown above, While during the T_{off} period, the inductor current will change from i_2 to i_1 . Now, talking about voltage, so during the turn on period, the voltage across the inductor will be equal to the supply input voltage, But when CH gets off then on applying KVL in the figure shown above, we will get,

$$V_L - V_0 + V_{in} = 0 \quad (II. 27)$$

This means,

$$V_L = V_0 - V_{in} \quad (II. 28)$$

Considering that output current is varying linearly, the energy input provided by the source to the inductor, when CH is on, is given as:

$$W_{on} = (\text{voltage across the inductor}) (\text{average current through the inductor}) T_{on}$$

$$W_{on} = V_{in} \left(\frac{i_1 + i_2}{2} \right) T_{on} \quad (II. 29)$$

Further, the energy that the inductor releases to the load when CH is off is given as:

$W_{\text{off}} = (\text{voltage across the inductor}) (\text{average current through the inductor}) T_{\text{off}}$

$$W_{\text{off}} = V_{\text{out}} - V_{\text{in}} \left(\frac{i_1 + i_2}{2} \right) T_{\text{off}} \quad (\text{II. 30})$$

For a lossless system, comparing the two energies, we will have,

$$V_{\text{in}} \left(\frac{i_1 + i_2}{2} \right) T_{\text{on}} = V_{\text{out}} - V_{\text{in}} \left(\frac{i_1 + i_2}{2} \right) T_{\text{off}} \quad (\text{II. 31})$$

On simplifying,

$$V_{\text{in}} T_{\text{on}} = V_{\text{out}} T_{\text{off}} - V_{\text{in}} T_{\text{off}} \quad (\text{II. 32})$$

$$V_{\text{out}} T_{\text{off}} = V_{\text{in}} T_{\text{on}} + V_{\text{in}} T_{\text{off}} \quad (\text{II. 33})$$

$$V_{\text{out}} T_{\text{off}} = V_{\text{in}} (T_{\text{on}} + T_{\text{off}}) \quad (\text{II. 34})$$

Since we know, $T = T_{\text{on}} + T_{\text{off}}$, therefore,

$$V_{\text{out}} T_{\text{off}} = V_{\text{in}} T \quad (\text{II. 35})$$

$$V_{\text{out}} = V_{\text{in}} \frac{T}{T_{\text{off}}} \quad (\text{II. 36})$$

$$V_{\text{out}} = V_{\text{in}} \frac{T}{T - T_{\text{on}}} \quad (\text{II. 37})$$

$$V_{\text{out}} = V_{\text{in}} \frac{1}{\left(\frac{T}{T} - \frac{T_{\text{on}}}{T} \right)} \quad (\text{II. 38})$$

Since, we know, duty cycle i.e., $\alpha = T_{\text{on}} / T$

$$V_{\text{out}} = V_{\text{in}} \frac{1}{(1 - \alpha)} \quad (\text{II. 39})$$

Thus, we can conclude here that the average load voltage can be stepped up with the change in the duty cycle.

II-6- Buck-Boost Converter:

The Buck-Boost Converter is a highly versatile class of DC-DC converter capable of producing an output voltage magnitude that is either greater than or less than the input voltage magnitude. Much like a transformer functions in AC circuits to adjust potential levels, the buck-boost converter "steps" the DC voltage to the desired level, regardless of whether that level is higher or lower than the source. In terms of architectural complexity, it is often viewed as the single inductor equivalent of a fly back converter, utilizing a simpler design to achieve a wide range of output regulation.

This converter frequently referred to in power electronics as a universal chopper operates based on its duty cycle, denoted as DA. By modulating this ratio, the system can seamlessly transition between step down and step up modes, providing an adaptable solution for applications with highly variable input sources or shifting load requirements. The

fundamental schematic of a typical Buck-Boost converter, illustrating the unique inverted polarity of its output, is provided below:




Figure (II.11): The Circuit Representation of Buck-Boost Converter

The input voltage source is connected to a solid state device, The second switch used is a diode, The diode is connected, in reverse to the direction of power flow from source.

to a capacitor and the load and the two are connected in parallel as shown in the figure above.

The controlled switch in the converter uses Pulse Width Modulation (PWM) to toggle on and off, PWM may operate based on time or frequency, with time based being the more common approach.

Frequency based modulation, though versatile, has the disadvantage of requiring a wide range of frequencies to precisely control the switch and thus achieve the desired output voltage.

Time based Modulation is mostly used for DC-DC converters, It is simple to construct and use.

The frequency remains constant in this type of PWM modulation, The Buck Boost converter has two modes of operation, The first mode is when the switch is on and conducting.

Mode I: Switch is ON, Diode is OFF




Figure (II.12): The Equivalent Circuit of Mode I

When the switch is in the ON state, it ideally functions as a short circuit, offering zero resistance and allowing current to flow from the DC source directly through the inductor before returning to the source. During this interval, the inductor charges, storing energy within its magnetic field. Because the diode is reverse biased during this phase, the inductor is effectively isolated from the output stage, and the load is temporarily supported by the energy stored in the output capacitor.

Once the solid state switch transitions to the OFF state, the inductor's magnetic field begins to collapse, causing its voltage polarity to reverse instantaneously. This reversal forward biases the diode, creating a new conduction path that forces the stored energy through the load and the capacitor. Crucially, while the voltage polarity across the inductor flips, the direction of the current through the inductor remains the same. This continuous current flow is what facilitates the transfer of energy to the load, regardless of whether the final output voltage is stepped up or stepped down relative to the input.

Let us say the switch is on for a time T_{ON} and is off for a time T_{OFF} .

We define the time period, T , as:

$$T = T_{ON} + T_{OFF} \quad (II. 40)$$

and the switching frequency:

$$f_{\text{switching}} = \frac{1}{T} \quad (II. 41)$$

Let us now define another term, the duty cycle:

$$D = \frac{T_{ON}}{T} \quad (II. 42)$$

Let us analyse the Buck Boost converter in steady state operation for this mode using KVL.

$$\begin{aligned} V_{in} &= V_L \\ V_L &= L \frac{di_L}{dt} = V_{in} \\ \frac{di_L}{dt} &= \frac{\Delta i_L}{\Delta t} = \frac{\Delta i_L}{DT} = \frac{V_{in}}{L} \end{aligned} \quad (II. 43)$$

Since the switch is closed for a time $T_{ON} = DT$ we can say that $\Delta t = DT$.

$$(\Delta i_L)_{\text{closed}} = \left(\frac{V_{in}}{L} \right) DT \quad (II. 44)$$

While performing the analysis of the Buck-Boost converter we have to keep in mind that

- The inductor current is continuous and this is made possible by selecting an appropriate value of L .
- The inductor current in steady state rises from a value with a positive slope to a maximum value during the ON state and then drops back down to the initial value with a negative slope. Therefore, the net change of the inductor current over any one complete cycle is zero.

Mode II: Switch is OFF, Diode is ON




Figure (II.13): The Equivalent Circuit of Mode II

In this mode, the inductor's polarity reverses as it transitions from an energy consumer to an energy provider. The energy accumulated in the previous cycle is now released and transferred to the load resistance; this discharge mechanism ensures that the current maintains its original direction through the load, providing the necessary continuity for stable operation. In a boost configuration, the inductor effectively acts as a secondary source in series with the input, "stacking" its potential to step up the output voltage. For the purpose of mathematical modeling and circuit analysis, we maintain the original sign conventions, allowing us to apply Kirchhoff's Voltage Law (KVL) consistently across both switching states to derive the converter's transfer function.

II-7- Buck Boost Converter Formula

Let us now analyze the Buck Boost converter in steady state operation for Mode II using KVL.

$$V_L = V_o \quad (II. 45)$$

$$V_L = L \frac{di_L}{dt} = V_o \quad (II. 46)$$

$$\frac{di_L}{dt} = \frac{\Delta i_L}{\Delta t} = \frac{\Delta i_L}{(1-D)T} = \frac{V_o}{L} \quad (II. 47)$$

Since the switch is open for a time

$$T_{OFF} = T - T_{ON} = T - DT = (1 - D)T \quad (\text{II. 48})$$

we can say that

$$\Delta t = (1 - D)T \quad (\text{II. 49})$$

$$(\Delta i_L)_{\text{open}} = \left(\frac{V_o}{L}\right)(1 - D)T \quad (\text{II. 50})$$

It is already established that the net change of the inductor current over any one complete cycle is zero.

$$(\Delta i_L)_{\text{closed}} + (\Delta i_L)_{\text{open}} = 0 \quad (\text{II. 51})$$

$$\left(\frac{V_o}{L}\right)(1 - D)T + \left(\frac{V_{\text{in}}}{L}\right)DT = 0 \quad (\text{II. 52})$$

$$\frac{V_o}{V_{\text{in}}} = \frac{-D}{1 - D} \quad (\text{II. 53})$$

We know that D varies between 0 and 1, If $D > 0.5$, the output voltage is larger than the input; and if $D < 0.5$, the output is smaller than the input, But if $D = 0.5$ the output voltage is equal to the input voltage[8].

II-8- Comparison of Converter Types:

Table (II.1) summarizes the voltage gains and switch stresses for the different converter types, For these converters, the evolution of the voltage gains as a function of the duty cycle is shown, While several types can be considered as boost converters, particularly if the duty cycle is greater than 0.5, only the boost type provides a boosting capability over the entire duty cycle range, For a duty cycle of 0.5 for example, the boost converter exhibits an output voltage twice the input voltage, Whereas for the other boost derived type, the output voltage is equal to the input voltage for this duty cycle value, It is only when the duty cycle approaches 1 that the other boost derived types tend to resemble the behavior of the conventional boost type.[9].

Converter /Parameters	Voltage Gain $\frac{V_{\text{out}}}{V_{\text{in}}}$	Voltage Controls $V_{k,\text{max}} = V_{d,\text{max}}$	Current Controls $i_{k,\text{max}} = V_{d,\text{max}} = i_{d,\text{max}}$
Boost	$\frac{1}{1 - \alpha}$	$\frac{V_{\text{in}}}{1 - \alpha} + \frac{\Delta V_{\text{out}}}{2}$	$\frac{I_{\text{out}}}{1 - \alpha} + \frac{\Delta I_L}{2}$

Buck	$\frac{\alpha}{1-\alpha}$	$\frac{V_{in}}{1-\alpha} + \frac{\Delta V_{out}}{2}$	$\frac{VC}{1-\alpha} + \frac{\Delta V_{out}}{2}$
Buck-Boost	α	V_{in}	$i_L + \frac{\Delta I_L}{2}$

Table (II.1): Comparison of Converter Types.

II-9- Efficiency of Static Converters:

The table provides insight into the efficiency of some well-known converter types.[10]

Structure	Conversion Efficiency	Battery
Boost	92%	24V
Buck	93%	12V
Buck-Boost	92%	12-24V

Table (II.2): Efficiency of Static Converters.

II-10- Conclusion:

In conclusion, DC-DC converters are the backbone of modern power electronics, providing the necessary efficiency and precision to manage energy across a vast spectrum of voltage requirements, By utilizing fundamental topologies like the Buck, Boost, and Buck-Boost converters, engineers can tailor power delivery to suit the unique demands of specific electronic architectures, ensuring that energy is never wasted during the conversion process.

These converters find wide ranging applications in industries such as automotive, renewable energy, telecommunications, and consumer electronics, From powering small electronic devices to managing energy flow in solar power systems, DC-DC converters are indispensable.

Building on this foundation of power conversion, the next logical progression is the optimization of energy harvest, Maximum Power Point Tracking (MPPT) stands as a vital technology in this regard, particularly within the renewable energy sector, By dynamically adjusting the electrical operating point of photovoltaic panels, MPPT ensures the extraction of the highest possible wattage regardless of environmental fluctuations, In the following chapter, we will explore the mechanics of MPPT, its critical role in system efficiency, and the various algorithms used to implement it

Chapter III

Maximum Power Point

Tracking

III-1- Introduction:

To enhance the inherent performance of solar panels and achieve peak conversion efficiency, a holistic optimization of the entire photovoltaic (PV) system is required. Central to this strategy is the refinement of the DC/DC converter, which serves as the critical interface between the PV generator and the load. By integrating a Maximum Power Point Tracking (MPPT) controller, the system can continuously extract the maximum available power, ensuring that the PV array operates at its Maximum Power Point (MPP) without energy dissipation. This dynamic regulation allows for the consistent capture of energy, successfully adapting to the unpredictable nature of atmospheric conditions, such as fluctuations in irradiance and temperature.

Since the 1970s, a diverse array of MPPT control methodologies has emerged, evolving from rudimentary voltage and current feedback loops into highly sophisticated algorithmic solutions. These modern controllers are engineered to autonomously calculate the system's MPP with high precision, representing a significant leap in our ability to harness solar energy reliably. Among the most prevalent techniques established in the field are the Incremental Conductance (INC) method, the Perturb and Observe (P&O) method, and the "hill climbing" algorithm [11]. Each of these approaches reflects a unique engineering solution to the challenge of maximizing energy yield in an ever changing environment.

III-2- Maximum Power Point Tracking:

The enhancement of photovoltaic (PV) system efficiency necessitates the maximization of the PV generator's power output. This is achieved through the precise selection of the operating point, effectively adapting the load impedance to the characteristics of the voltage source. Within this architecture, the DC-DC converter functions as an indispensable impedance adapter, ensuring the system remains anchored at the optimal point to facilitate peak power production [12]. This synchronization between source and load is fundamental to transforming raw solar energy into a stable and usable electrical resource.

Consequently, maximizing the output of a photovoltaic source involves a continuous pursuit of this optimal operating state, a process formally recognized as Maximum Power Point Tracking (MPPT). These MPPT methodologies utilize iterative search algorithms to determine the solar module's ideal coordinates, ensuring

maximal power generation without necessitating a disruption in system operation, By calculating the extracted power through the real time multiplication of measured current and voltage, these various methods can dynamically pursue the true Maximum Power Point (MPP), While several control strategies exist including the constant voltage, constant current, and incremental conductance methods this work focuses on the Perturb and Observe (P&O) algorithm, This particular method was selected for its elegant simplicity and the practical ease with which it can be implemented in real world energy systems.

III-3- Working principle of MPPT:

Specific control laws have been developed to drive devices toward the peak operating points of their characteristic curves, even when these points are not predetermined or when the underlying causes for their fluctuations remain unknown, Within the context of energy harvesting, these optimal states are identified as maximum power points, This control paradigm is widely recognized in technical literature as "Maximum Power Point Tracking," or simply MPPT, The core principle of such control schemes is to execute a dynamic search for the Maximum Power Point (MPP), ensuring a seamless impedance adaptation between the generator and its load to facilitate the transfer of maximum available power [13].

To streamline the operational analysis of this control mechanism, a DC load is typically selected as the reference, As observed in this power chain, the MPPT controller must be coupled with a four pole network possessing sufficient degrees of freedom to enable the necessary adaptation between the PV generator and the load, In photovoltaic conversion systems, this four pole interface is realized through a DC-DC converter; this configuration ensures that the output provided by the PV generator consistently aligns with its theoretical maximum power (P_{MAX}), which is then effectively transferred to the designated load.




Figure (III.1): Block Diagram of The PV System

A prevalent control strategy involves the automatic modulation of the duty cycle to steer the generator toward its optimal operating value, a necessary intervention given the sudden load variations that can manifest at any moment. As depicted in Figure (III.2), three distinct categories of disturbances are identified which shift the operating state from the initial maximum power point (MPP1) to a secondary point (P1), deviating from the optimum. In instances of fluctuating solar irradiance (case a), the system must dynamically recalibrate the duty cycle to converge upon the new MPP2. Similarly, during a load variation (case b), the operating point undergoes a shift that can be corrected to a new optimal position through active command intervention. To a more subtle degree, shifts may occur due to thermal variations in the photovoltaic module's operating temperature (case c). While this requires a corresponding command response, it is distinct in that it does not share the same urgent time constraints as the former two cases [14].




Figure (III.2): Search and Recovery Of MPP

III-4- Classification of MPPT Control:

In a broader sense, MPPT controllers are categorized based on their electronic architecture, falling into analog, digital, or hybrid implementations. However, a more insightful classification is derived from the specific nature of the search mechanism they employ and the distinct input parameters utilized by the controller to navigate the power curve.

III-4-1- Classification of MPPT Controllers Based on Input Parameters:

a) MPPT Controllers Operating from Input Parameters:

A diverse array of MPPT controllers has been developed to execute a maximum power point search by monitoring the dynamic evolution of power delivered by the PV array. Prominent examples include the Perturb and Observe (P&O) method and incremental conductance algorithms, both of which analyse the power output to initiate precise control actions for successful tracking. Additionally, some controllers utilize proportional relationships between the optimal parameters of the maximum power point specifically V_{opt} and I_{opt} and the fundamental characteristic parameters of the PV module, such as the open circuit voltage (V_{oc}) and short circuit current (I_{sc}). This methodological variety allows for a sophisticated approach to power management, ensuring the system can adapt its search strategy to the unique electrical signature of the PV source.

Notably, MPPT controllers inspired by the architecture of neural networks also fall within this category, representing a more advanced tier of intelligence. These systems either utilize extensive memory structures to store and reference a vast library of potential operating scenarios or rely on refined approximation techniques to navigate the power curve. Such controllers are highly valued for their superior precision and rapid transient response times, bridging the gap between standard algorithmic logic and adaptive computational intelligence [15].

b) MPPT Controllers Operating from Output Parameters of the Converter:

In the academic literature, alternative algorithms have been developed that focus on the output parameters of the DC-DC converter to guide the tracking process. A primary example includes MPPT controllers designed to maximize the output current, a strategy predominantly utilized when the system load is a battery. In such configurations, an approximation of P_{max} is derived through the operational efficiency

of the conversion stage; essentially, the integrity of this approximation is directly proportional to the quality and efficiency of the converter itself. However, it is important to note that single sensor systems generally possess an inherent degree of imprecision compared to dual parameter sensing. Interestingly, many of these streamlined systems were originally pioneered for the rigorous and resource constrained requirements of space applications [15].

III-4-2- Classification of MPPT Controllers According to the Type of Search:

a) Indirect MPPT:

This category of MPPT control exploits the inherent correlation between easily measurable variables, such as the open circuit voltage (V_{oc}), and the estimated position of the Maximum Power Point. It encompasses control strategies that derive the PV system's operating point from predefined parametric models, as well as methods that establish optimal voltage tracking by solely monitoring cell temperature fluctuations via a single sensor. These strategies are characterized by their straightforward implementation, offering a pragmatic solution for energy management. Consequently, they are primarily intended for cost effective, lower precision systems deployed in geographical regions characterized by stable climatic conditions and minimal environmental variance [16].

b) Direct MPPT:

This category of MPPT control identifies (MPP) the optimal operating point by analyzing real-time measurements of system currents, voltages, or power levels, enabling a dynamic response to unpredictable fluctuations within the photovoltaic environment. These procedures typically employ a search algorithm that tracks the peak of the power curve without necessitating any interruption to system performance. In practice, the operating voltage is adjusted at fixed intervals: if the subsequent power output increases, the search maintains its trajectory, if it decreases, the direction is reversed. While this leads to a characteristic oscillation around the true MPP, the fundamental logic remains a robust framework for energy maximization. To mitigate interpretation errors such as those triggered by rapid surges in solar irradiance that might mislead the search direction more advanced iterations of these algorithms are often employed.

Accurately pinpointing the PV generator's power requires the simultaneous measurement of voltage and current followed by the multiplication of these two variables, a process central to modern tracking intelligence. Beyond simple incremental logic, other sophisticated algorithms introduce small-signal sinusoidal perturbations into the converter's switching frequency. By comparing the alternating and direct components of the PV system's voltage, these methods can precisely position the operating point in the immediate vicinity of the MPP. This class of control is highly regarded in the field for its superior precision and rapid transient response, bridging the gap between basic automation and highly adaptive power electronics [16].

III-5- Different MPPT Commands Synthesis:

A significant volume of research regarding MPPT control strategies has emerged consistently in the literature since 1968, marking the initial publication of control laws specifically adapted for photovoltaic renewable energy systems. This foundational period initiated a rapid evolution in power electronics, as engineers sought to master the volatile nature of solar energy. Given the extensive proliferation of publications within this specialized field, it is essential to establish a systematic classification of various MPPT techniques. By categorizing these methods according to their fundamental operating principles.

III-5-1- First MPPT Commands Types:

The algorithms integrated into the earliest MPPT commands were characterized by a relative simplicity, necessitated by the limited computational capacity of the microcontrollers available during that era. Furthermore, initial applications predominantly situated within the aerospace sector faced less volatile fluctuations in temperature and solar irradiance compared to contemporary terrestrial systems. The pioneering command law applied to a photovoltaic system was first detailed by A.F. Boehringer, utilizing an adaptive control framework designed to maintain the system at its maximum power point (MPP). This logic, as illustrated in Figure 3, represents a foundational approach that can be readily translated into a computational routine.

The operational sequence involves the real-time calculation of power at a specific interval (t_i) derived from the instantaneous measurements of I_{PV} and V_{PV} . This value is then compared against the power signature captured at the preceding

interval (t_i-1) and stored in memory, Based on the differential between these two states, the controller calculates and implements a revised duty cycle (D) within the static converter.




Figure (III.3): Bloc Diagram of a Digital MPPT Command

While this foundational principle remains theoretically robust, it has been significantly refined through integration into the highly efficient numerical algorithms. Although the core logic of the search persists, contemporary implementations have achieved substantial advancements in both response latency and the precision of the Maximum Power Point (MPP) localization [14].

III-5-2- Efficient MPPT Commands Algorithms:

The four (04) methodologies most frequently encountered in the field are generally categorized as Hill Climbing, Perturb and Observe (P&O), Incremental Conductance, and Artificial Neural Networks (ANN). These techniques represent the primary architectural pillars of modern power management, each offering a distinct approach to navigating the complexities of energy optimization.

III-5-3- Algorithm Perturb and Observe (P&O):

The operational philosophy of Perturb and Observe (P&O) control involves introducing a small amplitude disruption to the voltage V_{PV} , relative to its current state, followed by a systematic analysis of the resulting power variation, PPV . As illustrated in Figure (III.4), this feedback loop allows the system to determine its relative position on the power curve: if a positive voltage increment leads to a rise in power, the operating point is situated to the left of the Maximum Power Point (MPP). Conversely, if a power reduction is observed following an increase in voltage, it indicates that the system has surpassed the peak and is now operating on the right-hand side of the MPP.




Figure (III.4): Ppv VS Vpv Characteristic of a Solar Panel

Figure (III.5) delineates the algorithmic structure of a conventional Perturb and Observe (P&O) MPPT controller, where the power trajectory is evaluated following each deliberate voltage disturbance. This specific command architecture necessitates the integration of two distinct sensors measuring current and voltage to calculate the solar generator's power output at every discrete moment. Currently, the P&O method remains a predominant choice in the industry, largely due to its straightforward implementation and minimal computational requirements. However, this simplicity introduces inherent challenges, most notably the steady state oscillations around the Maximum Power Point (MPP). Because the algorithm must periodically re execute its search to confirm the peak, the system is trapped in a state of continuous fluctuation, never truly settling on the optimal coordinate.




Figure (III.5): Divergence of The P & O Command Due to Radiation Variations




Figure (III.6): Algorithm of The P & O Type of Command

To illustrate this phenomenon, consider a scenario under a specific solar irradiance level, E1, with the initial operating point situated at A. Following a voltage perturbation of magnitude ΔV , the system transitions to point B; in a stable

environment without changes in illumination, this results in a detected negative power derivative, This detection triggers a reversal of the perturbation direction, establishing an equilibrium characterized by continuous oscillations around the MPP as the operating point fluctuates between B and C, It is important to observe that the resulting power transfer losses will vary in significance based on the proximity of points B and C to the optimal point A. However, if the irradiance shifts from E1 to E2 during this process, the operating point moves from A to D. The algorithm interprets this shift as a positive power variation, which can momentarily mislead the tracking logic as it attempts to distinguish between a successful perturbation and a change in environmental conditions [14].

III-5-4- Algorithm Hill Climbing :

The hallmark of the Hill Climbing MPPT method is its inherent simplicity, leveraging the duty cycle of the boost converter as the primary control parameter to execute the tracking process [17],[18]. However, the principal drawback of this technique lies in the delicate trade off required to maintain system stability during periods of constant irradiance. Furthermore, the method often struggles with response latency when faced with abrupt atmospheric fluctuations [17],[18]. During steady state conditions, an exceptionally small duty cycle variation, ΔD , is necessary to minimize power oscillations around the peak and prevent significant energy loss. Conversely, when solar radiation changes rapidly, a larger duty cycle increment is required to accelerate the pursuit of the new maximum power point, creating a fundamental conflict between precision and agility.




Figure (III.7): State Flowchart of Hill Climbing MPPT Technique.

III-5-5- Algorithm Incremental conductance (INC) :

The operational principle of this algorithm is based on the comparative analysis of the instantaneous conductance, $G = I/V$, and the incremental conductance, dG , to precisely determine the operating point's location relative to the maximum power point. If the incremental conductance is greater than the negative of the instantaneous conductance ($dG > -G$), the system identifies that it is to the left of the peak, and the duty cycle is subsequently decreased. Conversely, if the incremental conductance is less than the negative of the instantaneous conductance ($dG < -G$), the duty cycle is increased. This iterative adjustment continues until the condition $dG = -G$ is satisfied, signaling that the maximum power point has been successfully achieved [19]. This method offers a more mathematically grounded approach to tracking, seeking to eliminate the hesitation often found in simpler trial and error logic.




Figure (III.8): Flowchart for The Incremental Conductance Algorithm.

III-5-6- Artificial Neural Networks (ANN) :

In a general sense, an artificial neural network (ANN) functions through the coordination of numerous processors operating in parallel, organized into a hierarchical layer structure. The initial input layer acts as the primary receptor for raw data, functioning much like the way optic nerves receive visual stimuli in the human biological system. Following this initial intake, each subsequent hidden layer receives and refines the processed information transmitted from the preceding stage. This architecture mirrors the human neurological experience, where individual neurons receive signals from those positioned closer to the sensory source. Finally, the terminal layer synthesizes these collective signals to generate the system's ultimate results or control outputs, transforming complex data into a singular, actionable decision.




Figure (III.9): Functioning of Artificial Neural Networks

Neural networks empower computational systems to autonomously acquire knowledge from novel datasets through sophisticated learning algorithms. Rather than relying on rigid, pre-defined instructions, these systems are trained on labeled datasets to master complex tasks, such as object recognition, by iteratively identifying and reinforcing underlying patterns. This departure from traditional programming means that neural networks cannot be directly scripted; instead, they evolve their internal logic in a manner strikingly similar to the cognitive development of a child's brain. This adaptive growth is typically achieved through three primary learning methodologies, which allow the network to refine its predictive accuracy and decision-making capabilities over time:

1- Supervised Learning: Within this framework, the algorithm undergoes training on a comprehensive dataset of labeled inputs and outputs, iteratively refining its internal parameters until it consistently achieves the target performance. In the context of MPPT, this involves presenting the network with specific environmental conditions such as varying irradiance and temperature paired with their known optimal operating points. By minimizing the error between its predictions and these established "ground truth" values, the network develops a robust mapping function that allows it to predict the maximum power point for new, unseen data with high precision.

2- Unsupervised Learning: In this methodology, the network operates on unlabeled datasets, autonomously identifying hidden structures or clusters within the information without the guidance of pre-established "correct" answers. A specifically designed cost function serves as the system's internal compass, steering the network toward the desired result by quantifying and penalizing deviations from the objective.

3 Reinforcement Learning: In this paradigm, the network evolves by interacting dynamically with its environment, receiving metaphorical rewards for positive outcomes and penalties for erroneous actions. This feedback loop empowers the controller to iteratively refine its strategy and enhance performance over time, mirroring the fundamental way humans acquire expertise by learning from their mistakes.

III-6- Application of Artificial Neural Networks in MPPT:

Artificial neural networks are increasingly employed to optimize Maximum Power Point Tracking (MPPT), a sophisticated and essential component of modern photovoltaic (PV) systems. By continuously modulating the operating parameters of the PV panels, these neural architectures significantly enhance the efficiency of solar energy capture, ensuring that the system consistently operates at its peak output potential. This dynamic adjustment is particularly vital as it accounts for highly variable environmental factors, including fluctuating solar irradiance, temperature gradients, and the complex challenges posed by partial shading. Through this high-level adaptive control, neural network-based MPPT empowers PV systems to harness solar energy with far greater efficacy, ultimately resulting in a substantial increase in cumulative energy production.

This example shows the use and practical application of artificial neural networks and their valuable role in improving the performance of PV systems through MPPT algorithms[20].

III-7- Implementation of ANN in MATLAB/SIMULINK:

The Neural Network Fitting app in MATLAB provides a user-friendly interface for designing, training, and evaluating artificial neural networks. The process involves selecting the data, configuring the network architecture, training the network, and assessing its performance through various plots and metrics. This tool is particularly useful for tasks like MPPT, where accurate modeling of complex relationships between inputs and outputs is crucial.

❖ Data Collection:

The initial phase of the proposed method involves collecting data from MPPT method simulations performed under a variety of scenarios. Data collection is the cornerstone for training and evaluating the ANN-based MPPT model[20].

❖ Setting Up the Neural Network Fitting Tool:

To begin the implementation process, we will open the Neural Network Fitting Tool in MATLAB. This tool provides a user-friendly interface for training and evaluating neural networks. We will import our defined variables and configure the tool for our specific application[21].




Figure (III.10): Setting Up the Neural Network Fitting Tool

This figure introduces the Neural Network Fitting app, explaining its purpose, which is to solve an input-output fitting problem using a two-layer feed-forward neural network.




Figure (III.11): Neural Network Structure

The diagram shows the structure of the neural network, which includes an input layer, hidden layers, and an output layer.

- **Training Algorithm:** It mentions that the network will be trained using the Levenberg-Marquardt backpropagation algorithm (trainlm).

1. Select Data:




Figure (III.12): Select Data

- **Inputs and Targets:** This figure allows you to select the input and target data from the MATLAB workspace.
- **Data Summary:** The summary on the right shows the dimensions of the selected data. Here, 'simple fit Inputs' and 'simple fit Targets' are used as example datasets, with 94 samples each.

2. Import Data:




Figure (III.13): Import Data

- **Data Import:** If the data is not already in the workspace, this figure allows you to browse and import data files from your computer. This ensures that the input and target datasets are correctly loaded into MATLAB for network training.

3. Validation and Test Data:




Figure (III.14): Validation and Test Data

- **Data Division:** This figure divides the dataset into training, validation, and testing subsets. The default division is 70% training, 15% validation, and 15% testing.
 - **Explanation:** Training data is used to train the network, validation data is used to prevent overfitting by stopping training when performance worsens, and testing data is used to independently assess the network's performance.
4. **Network Architecture:**




Figure (III.15): Network Architecture

- **Hidden Layer Configuration:** This figure allows you to set the number of neurons in the hidden layer(s). In this example, there are 10 neurons in the hidden layer[21].

Chapter III: Maximum Power Point Tracking

- **Network Diagram:** The diagram below visually represents the structure of the network with the specified number of hidden neurons.

5. Network Training:




Figure (III.16): Network Training

Training Process: This figure shows the progress of the network training, including the number of epochs, performance, gradient, and validation checks.

Performance Plots: Various plots are available to monitor the training process, including performance, training state, error histogram, and regression plots.

Stop Training: You can manually stop the training process if needed[22].

6. Train Network :




Figure (III.17): Train Network

- **Training Results:** After training, this figure shows the results, including the mean squared error (MSE) for the training, validation, and testing datasets.

- **Regression Plot:** This plot shows the correlation between the network outputs and the targets. A high R-value close to 1 indicates a good fit.
- **Error Histogram:** This plot shows the distribution of errors between the network outputs and the targets[22].

III-8- Conclusion:

In this chapter, we have embarked upon the most critical and complex phase of our investigation: the presentation of the fundamental principles governing the search for the maximum power point. By establishing a comprehensive classification of various MPPT control strategies, we have systematically explored the methodologies most frequently documented in the scientific literature, The sheer diversity of these command laws underscores the fact that this field of research remains in a state of constant evolution

Chapter IV

Simulation Results

IV-1- Introduction:

In this chapter, a comparative performance evaluation is conducted on four prominent Maximum Power Point Tracking (MPPT) algorithms Perturb and Observe (P&O), Incremental Conductance (INC), Artificial Neural Network (ANN), and Fuzzy Logic Controller (FLC) which optimize photovoltaic systems by continuously adjusting the operational point to extract maximum energy, thereby significantly enhancing overall efficiency and energy yield. While the P&O algorithm relies on periodic perturbations and observation patterns to climb the power curve, the INC technique utilizes incremental conductance for more refined adjustments, whereas the AI-driven ANN method achieves high-precision tracking by identifying the maximum point through learned data patterns rather than simple measurements, and finally, the FLC employs heuristic fuzzy rules to effectively manage nonlinearities and environmental uncertainties, resulting in a comprehensive analysis that highlights the specific merits and demerits of each approach to help determine the most suitable algorithm for varying operating conditions.

IV-2- Parameters of System Simulation:

The following characteristics of panel and the parameters of boost converter that are used in our system simulation, are shown in the figure and table below:

Module data	
Module:	User-defined
Maximum Power (W)	200.22
Cells per module (Ncell)	60
Open circuit voltage Voc (V)	57.6
Short-circuit current Isc (A)	4.6
Voltage at maximum power point Vmp (V)	47
Current at maximum power point Imp (A)	4.26
Temperature coefficient of Voc (%/deg.C)	-0.35502
Temperature coefficient of Isc (%/deg.C)	0.06

Figure (IV.1): Characteristics of Panel

Boost Converter	Value
Capacitor 1	200 μ F
Inductor	3.5 mH
Capacitor 2	100 μ F
Resistive Load	300 Ω

Table (IV.1): Parameters of Boost Converter

IV-3- Simulation Results:

IV-3-1- P&O Algorithm:

In this simulation, the Perturb and Observe (P&O) algorithm was implemented to evaluate the output performance in terms of power, voltage, and current, as illustrated in the general system simulation depicted in Figure (IV.2). This figure showcases the comprehensive setup of the P&O-based MPPT system, detailing the seamless integration of the photovoltaic (PV) panels with the controller, which dynamically modulates the duty cycle of the DC-DC converter to maintain the operating point at its maximum potential. By observing the resulting power shifts following periodic perturbations, the simulation highlights how the system effectively tracks the optimal energy extraction point, thereby validating the P&O algorithm's practical performance under the specified simulation parameters.




Figure (IV.2): Schema of System Simulation With P&O

a) Constant Irradiance (1000 W/m^2) :




Figure (IV.3): Duty Cycle Simulation Result

Chapter IV: Simulation Results

Figure (IV.3) illustrates the dynamic behavior of the MPPT system's duty cycle, providing both a global perspective on system stability and a detailed, zoomed-in view that captures the critical, high-frequency oscillations essential for precise MPPT tracking. This granular analysis highlights how the controller continuously adjusts the duty cycle to remain locked onto the maximum power point, revealing the characteristic "perturbation" patterns that define the algorithm's steady-state operation.




Figure (IV.4): Power Simulation Result

Figure (IV.4) illustrates the power response of the MPPT system employing the P&O algorithm, featuring a main plot that captures a rapid initial ascent followed by stabilization at approximately 350W. The accompanying zoomed-in view highlights the inherent oscillatory nature of the power output a hallmark of the P&O algorithm as it continuously perturbs the system to maintain its lock on the maximum power point. These steady-state oscillations represent a calculated trade-off for ensuring optimal energy extraction and serve as a critical metric for evaluating the overall tracking efficiency and dynamic performance of the MPPT controller.




Figure (IV.5): Voltage Simulation Result

Figure (IV.5) illustrates the voltage response of the MPPT system utilizing the P&O algorithm, with the primary plot capturing a rapid initial rise followed by stabilization at approximately 320V. The accompanying zoomed-in view highlights the characteristic oscillatory nature of the voltage output, reflecting the continuous "searching" behavior of the controller as it modulates the operating point.




Figure (IV.6): Current Simulation Result

Figure (IV.6) illustrates the current response of the MPPT system employing the P&O algorithm, where the main plot captures a rapid transient phase that quickly stabilizes at approximately 1.05A, signaling that the system has successfully reached its maximum power point. The accompanying zoomed-in view provides a detailed look at the inherent oscillations around this steady-state value, which are the direct result of the controller's continuous perturbation cycles.

b) Variable Irradiances (1000, 900, 700, 1000 W/m²) :




Figure (IV.7): Power Simulation Result

Figure (IV.7) provides a comprehensive evaluation of the MPPT system's power output behavior under dynamic environmental conditions, specifically highlighting its response to varying irradiance levels. The primary plot demonstrates the system's robust tracking capabilities as it stabilizes at power levels of approximately 350 W, 330 W, 270 W, and returning to 350 W in response to irradiance shifts of 1000 W/m², 900 W/m², 700 W/m², and 1000 W/m², respectively, A red dashed ellipse and an accompanying zoomed-in view draw attention to the system's transient performance during sudden irradiance drops, capturing the characteristic oscillations as the P&O algorithm re-adjusts its search parameters to locate the new maximum power point, This detailed analysis underscores the efficiency and adaptability of the MPPT controller, proving its effectiveness in maintaining high energy yields during real time solar fluctuations.




Figure (IV.8): Voltage Simulation Result

Figure (IV.8) illustrates the dynamic voltage response of the MPPT system employing the P&O algorithm as it adapts to fluctuating irradiance levels. The primary plot depicts a rapid initial stabilization at approximately 320V, followed by distinct stepwise decreases that correspond to the reductions in solar intensity. Then it returns to its original state as the intensity of solar radiation increases. The accompanying zoomed-in view offers a detailed analysis of the transient fluctuations, capturing the algorithm's continuous "hill-climbing" adjustments as it recalibrates the operating voltage to ensure optimal performance.




Figure (IV.9): Current Simulation Result

Figure (IV.9) demonstrates the dynamic current response of the MPPT system as it adapts to fluctuating irradiance levels under the control of the P&O algorithm. The primary plot captures the current initially stabilizing at approximately 1A before exhibiting distinct stepwise decreases in direct correlation with diminishing solar intensity. Then it returns to its original state as the intensity of solar radiation increases. An accompanying zoomed-in view provides a detailed analysis of the transient response during these irradiance shifts, highlighting the characteristic oscillations as the controller recalibrates to maintain the maximum power point.

IV-3-2- Incremental Conductance:

In this simulation, the Incremental Conductance (INC) algorithm was implemented to evaluate the output performance in terms of power, voltage, and current, as illustrated in the general system simulation depicted in Figure (IV.10). This figure showcases the comprehensive setup of the INC-based MPPT system, detailing the seamless integration of the photovoltaic (PV) panels with the controller, which dynamically modulates the duty cycle to optimize power extraction. By utilizing the mathematical relationship between instantaneous and incremental conductance, the simulation highlights how the INC controller achieves a precise lock on the maximum power point, offering a sophisticated alternative to simpler perturbation methods by theoretically eliminating steady-state oscillations once the peak is reached.




Figure (IV.10): Schema of System Simulation With INC

c) Constant Irradiance (1000 W/m^2) :




Figure (IV.11): Power Simulation Result

Figure (IV.11) illustrates the power stabilization performance of the MPPT system managed by the Incremental Conductance (INC) algorithm, with the primary plot capturing a rapid initial rise followed by stabilization at approximately 370W, The accompanying zoomed-in view highlights the subtle periodic fluctuations, detailing the algorithm's continuous adjustments as it balances the incremental and instantaneous conductance to maintain an optimal power output, This high-precision tracking capability underscores the efficiency of the INC method, demonstrating its ability to dynamically lock onto the maximum power point with minimal steady-state deviation.

Chapter IV: Simulation Results




Figure (IV.12): Voltage Simulation Result

The Figure (IV.12) demonstrates the voltage response of an Incremental Conductance-based MPPT system. The main plot shows the voltage stabilizing around 330V, while the zoomed-in view captures small fluctuations.




Figure (IV.13): Current Simulation Result

Figure (IV.13) illustrates the current stabilization performance of the MPPT system under the management of the Incremental Conductance (INC) algorithm, with the primary plot capturing a rapid transient phase that stabilizes at approximately 1.1A. This steady-state current level serves as a clear indicator of the system's efficiency in successfully reaching the maximum power point, while the accompanying zoomed-in view reveals the characteristic small-scale fluctuations inherent in the digital control loop. By maintaining this precise current output in tandem with the stabilized voltage, the INC controller demonstrates its superior ability to provide a consistent and high-quality power flow to the load with minimal deviation from the optimal operating point.

d) Variable Irradiances (1000, 900, 700, 1000 W/m²) :




Figure (IV.14): Power Simulation Result

Figure (IV.14) illustrates the power response of the MPPT system utilizing the Incremental Conductance (INC) algorithm under dynamic irradiance conditions, with the primary plot depicting an initial stabilization at approximately 350W followed by distinct stepwise decreases as solar intensity diminishes. Then it returns to its original state as the intensity of solar radiation increases. The accompanying zoomed-in view captures the transient fluctuations during these irradiance shifts, highlighting the algorithm's sophisticated ability to rapidly recalibrate and track the new maximum power point with high precision. This responsive behavior demonstrates the robustness of the INC method in maintaining optimal energy extraction even during sudden environmental changes, ensuring the system operates at peak efficiency across a varying irradiance spectrum.




Figure (IV.15): Voltage Simulation Result

Figure (IV.15) illustrates the dynamic voltage response of the Incremental Conductance-based MPPT system as it adapts to fluctuating irradiance levels, with the

primary plot capturing a rapid initial rise and stabilization at approximately 330V, This is followed by distinct stepwise decreases that align with the reductions in solar intensity. Then it returns to its original state as the intensity of solar radiation increases, while the accompanying zoomed-in view highlights the transient fluctuations as the algorithm recalibrates the operating voltage.




Figure (IV.16): Current Simulation Result

Figure (IV.16) illustrates the dynamic current response of the MPPT system employing the Incremental Conductance (INC) algorithm, with the primary plot capturing an initial stabilization at approximately 1.1A followed by distinct stepwise decreases as irradiance levels diminish. Then it returns to its original state as the intensity of solar radiation increases. The accompanying zoomed-in view provides a detailed look at the transient fluctuations during these irradiance shifts, highlighting the algorithm's rapid recalibration to maintain the maximum power point.

IV-3-3- Artificial Neural Network (ANN):

In this simulation, we used the Artificial Neural Network (ANN) algorithm to obtain results for power, voltage, and current. Figure (IV.17) represents the general system simulation, showcasing the overall setup and performance of the ANN-based MPPT system. The figure illustrates the integration of PV panels with the ANN-based MPPT controller, which adjusts the duty cycle to optimize power extraction.




Figure (IV.17): Schema of System Simulation With ANN

e) Constant Irradiance (1000 W/m^2) :




Figure (IV.18): Duty Cycle Simulation Result

The Figure (IV.18) demonstrates the stability and fine-tuning of the duty cycle by an ANN-based MPPT system. The main plot shows a stable duty cycle near 1, while the zoomed-in view reveals periodic adjustments, indicating the ANN's responsiveness to optimize performance.




Figure (IV.19): Power Simulation Result

Chapter IV: Simulation Results

Figure (IV.19) illustrates the power stabilization performance of the MPPT system managed by the Artificial Neural Network (ANN) algorithm, with the primary plot capturing a rapid initial ascent and stabilization at approximately 380W. This high power level reflects the superior efficiency of the AI-driven approach, while the accompanying zoomed-in view reveals subtle periodic fluctuations that represent the ANN's real-time adjustments to maintain an optimal power output. By leveraging pre-trained data patterns to predict the ideal operating point, the ANN demonstrates a remarkable capability to dynamically track the maximum power point with high precision.




Figure (IV.20): Voltage Simulation Result

Figure (IV.20) illustrates the dynamic voltage response of the Artificial Neural Network (ANN)-based MPPT system, with the primary plot capturing a rapid initial ascent and stabilization at approximately 335V. This high-precision voltage regulation reflects the algorithm's trained capability to accurately identify the optimal operating point, while the accompanying zoomed-in view reveals the subtle, high-frequency fluctuations inherent in the neural network's continuous predictive adjustments.




Figure (IV.21): Current Simulation Result

The Figure (IV.21) shows the current stabilization of an ANN-based MPPT system. The main plot displays a rapid rise in current, stabilizing around 1.1A. The zoomed-in view highlights small fluctuations.

a) Variable Irradiances (1000, 900, 700, 1000 W/m²):




Figure (IV.22): Power Simulation Result

The Figure (IV.22) demonstrates how the ANN-based MPPT system adjusts its power output under varying irradiance conditions. The main plot shows the power stabilizing at approximately 350W initially, with stepwise decreases as the irradiance drops. Then it returns to its original state as the intensity of solar radiation increases. The zoomed-in view captures the transient fluctuations during an irradiance change.




Figure (IV.23): Voltage Simulation Result

The Figure (IV.23) illustrates the ANN-based MPPT system's voltage response to varying irradiance. The main plot shows the voltage stabilizing around 330V and stepping down with decreasing irradiance. Then it returns to its original state as the intensity of solar radiation increases. The zoomed-in view highlights transient

fluctuations. This demonstrates the algorithm's capability to dynamically adjust to real-time changes in solar irradiance, ensuring efficient performance.




Figure (IV.24): Current Simulation Result

The Figure (IV.24) demonstrates the current response of an ANN-based MPPT system under varying irradiance conditions. The main plot shows the current stabilizing around 1.1A initially, with stepwise decreases as the irradiance drops. Then it returns to its original state as the intensity of solar radiation increases. The zoomed-in view captures transient fluctuations during an irradiance change.

IV-4- Fuzzy Logic Controller (FLC) algorithm:

In this simulation, the Fuzzy Logic Controller (FLC) algorithm was implemented to evaluate the output performance in terms of power, voltage, and current, as depicted in the general system simulation in Figure (III.25). This figure illustrates the comprehensive architectural setup of the FLC-based MPPT system, detailing the seamless integration of the photovoltaic (PV) panels with the fuzzy controller, which dynamically modulates the duty cycle to optimize power extraction.




Figure (III.25): Schematic simulation system with FLC

a) Constant Irradiance (1000 W/m²):




Figure (III.26): Power simulation result

Figure (III.26) illustrates the system power output rapidly ascending to approximately 370W under constant irradiance, managed by a Fuzzy Logic Controller (FLC). Following this initial transient phase, the power maintains stability around the target value but exhibits continuous, relatively small-scale cyclical fluctuations during the steady-state period. The zoomed-in view emphasizes these oscillations, reflecting the inherent control dynamics and the iterative duty cycle adjustments characteristic of the FLC's membership function processing.




Figure (III.27): Voltage simulation result

Figure (III.27) illustrates the dynamic voltage response of the Artificial Neural Network (FLC)-based MPPT system, with the primary plot capturing a rapid initial ascent and stabilization at approximately 335V. This high-precision voltage regulation reflects the algorithm's trained capability to accurately identify the optimal operating point, while the accompanying zoomed-in view reveals the subtle, high-frequency fluctuations inherent in the neural network's continuous predictive adjustments.




Figure (III.28): Current simulation result

Figure (III.28) illustrates the current stabilization of the FLC-based MPPT system, where the primary plot depicts a rapid transient rise followed by stabilization at approximately 1.1A. This performance reflects the efficiency of the fuzzy controller under constant irradiance conditions, while the accompanying zoomed-in view highlights small-scale fluctuations near the stabilization point. These minor deviations are characteristic of the algorithm's rule-based nature, representing the continuous linguistic processing and duty cycle adjustments required to maintain the maximum power point.

b) Variable Irradiances (1000, 900, 700, 1000 W/m²):

Chapter IV: Simulation Results




Figure (III.29): Power simulation result

The Figure (III.29) demonstrates how the FLC-based MPPT system adjusts its power output under varying irradiance conditions. The main plot shows the power stabilizing at approximately 350W initially, with stepwise decreases as the irradiance drops. Then it returns to its original state as the intensity of solar radiation increases. The zoomed-in view captures the transient fluctuations during an irradiance change.




Figure (III.30): Voltage simulation result

The Figure (III.30) illustrates the FLC-based MPPT system's voltage response to varying irradiance. The main plot shows the voltage stabilizing around 330V and stepping down with decreasing irradiance. Then it returns to its original state as the intensity of solar radiation increases. The zoomed-in view highlights transient fluctuations. This demonstrates the algorithm's capability to dynamically adjust to real-time changes in solar irradiance, ensuring efficient performance.




Figure (III.31): Current simulation result

The Figure (III.31) demonstrates the current response of an FLC-based MPPT system under varying irradiance conditions. The main plot shows the current stabilizing around 1.1A initially, with stepwise decreases as the irradiance drops. Then it returns to its original state as the intensity of solar radiation increases. The zoomed-in view captures transient fluctuations during an irradiance change.

IV-5- Comparison and Analysis Between (P&O, INC, ANN, FLC):

IV-5-1- Constant Irradiance (1000 W/m^2):

The following figures compare the current and voltage outputs of three MPPT algorithms: Incremental Conductance (INC), Perturb and Observe (P&O), Artificial Neural Network (ANN), and Fuzzy Logic Control (FLC).




Figure (IV.25): Current Simulation Result




Figure (IV.26): Voltage Simulation Result

IV-5-2- Comparison:

- **Incremental Conductance (INC):** This algorithm shows rapid stabilization in both current and voltage with minimal fluctuations, indicating efficient and stable performance.
- **Perturb and Observe (P&O):** While it also achieves rapid stabilization, it exhibits more fluctuations in both current and voltage, indicating less stability compared to the other two algorithms.

- **Artificial Neural Network (ANN):** This algorithm achieves stabilization with minimal fluctuations, similar to INC, suggesting efficient and stable performance.
- **Fuzzy Logic Control (FLC):** The algorithm achieves rapid stabilization in both current and voltage with a highly responsive tracking capability. While it maintains efficient and stable performance throughout the simulation, it exhibits small-scale, periodic fluctuations during the steady-state phase, reflecting the continuous fine-tuning and rule-based adjustments inherent in its fuzzy inference system.

IV-5-3- Analysis:

In this comparative analysis, the Artificial Neural Network (ANN), Incremental Conductance (INC), and Fuzzy Logic Controller (FLC) demonstrate superior performance with minimal fluctuations in current and voltage, suggesting they are more stable and efficient in tracking the maximum power point compared to P&O. While the ANN might have a slight edge over the others due to its adaptive nature and potential for better optimization in varying conditions, the FLC provides a similarly robust and rapid response by effectively managing system non-linearities, despite exhibiting small-scale steady-state ripples.

Therefore, based on these figures, the Artificial Neural Network (ANN) algorithm appears to be the best option for MPPT, offering efficient stabilization with minimal fluctuations, closely followed by the Incremental Conductance (INC) and Fuzzy Logic Controller (FLC) algorithms.

IV-5-4- Variable Irradiances (1000, 900, 700, 1000 W/m²):




Figure (IV.27): Current Simulation Result




Figure (IV.28): Voltage Simulation Result

IV-5-5- Comparison:

- **Incremental Conductance (INC):** This algorithm shows rapid stabilization but exhibits more fluctuations and deviations during irradiance changes, indicating less stability compared to the other two algorithms.
- **Perturb and Observe (P&O):** This algorithm shows noticeable fluctuations and is less stable during transitions between irradiance levels.
- **Artificial Neural Network (ANN):** This algorithm exhibits the least fluctuations and the smoothest transitions during changes in irradiance, indicating the highest stability and efficiency.
- **Fuzzy Logic Control (FLC):** The algorithm demonstrates a robust ability to manage system non-linearities, characterized by an efficient response that stabilizes effectively under varying conditions. While it outperforms traditional methods in tracking speed, the zoomed-in analysis reveals small-scale, cyclical fluctuations near the stabilization point, reflecting the continuous linguistic processing and rule-based adjustments inherent in its design.

❖ Analysis:

In this comparative analysis, the Artificial Neural Network (ANN) algorithm demonstrates the most robust performance, characterized by minimal fluctuations and smooth transitions during varying irradiance levels, which signifies superior stability and efficiency. The ANN maintains a distinct advantage over the Incremental Conductance (INC) and Perturb and Observe (P&O) algorithms due to its adaptive nature and superior optimization in dynamic conditions, while the Fuzzy Logic Controller (FLC) offers a high-performance alternative that effectively manages

system non-linearities with a rapid response, though it exhibits slightly more steady-state ripple than the ANN.

Ultimately, based on these simulation results, the ANN algorithm emerges as the optimal choice for MPPT, providing the most stable and efficient performance across the entire spectrum of fluctuating irradiance conditions.

IV-6- Comparison of efficiency between algorithms (P&O, INC, ANN and FLC):

IV-6-1- Constant Irradiance (1000 W/m^2):

Algorithm	Efficiency
Perturb and Observe (P&O)	94.72%
Incremental Conductance (INC)	95.58%
Artificial Neural Network (ANN)	96.63%
Fuzzy Logic Controller (FLC)	93.18%

Table (IV.2): Table of Efficiency




Figure (IV.29): Chart of Efficiency

Under constant irradiance of 1000 W/m^2 , the Artificial Neural Network (ANN) algorithm demonstrates the highest efficiency, around 97%. The Incremental Conductance (INC) algorithm follows with an efficiency of about 96%, while the Perturb and Observe (P&O) algorithm has the lowest efficiency at approximately 95%. This indicates that the ANN algorithm is the most effective in optimizing power

Chapter IV: Simulation Results

output under stable irradiance conditions, outperforming both the INC and P&O algorithms.

IV-6-2- Variable Irradiances (1000, 900, 700, 1000 W/m²):

Algorithm	Efficiency
Perturb and Observe (P&O)	84.84%
Incremental Conductance (INC)	88.04%
Artificial Neural Network (ANN)	95.06%
Fuzzy Logic Controller (FLC)	91.79%

Table (IV.3): Table of Efficiency




Figure (IV.30): Chart of Efficiency

Under variable irradiance conditions, the Artificial Neural Network (ANN) algorithm demonstrates the highest efficiency, around 95%, indicating its superior ability to adapt to changing light conditions. The Incremental Conductance (INC) algorithm follows with an efficiency of about 89%, showing reasonable performance but less stability compared to ANN. The Perturb and Observe (P&O) algorithm has the lowest efficiency at approximately 86%, reflecting its greater susceptibility to fluctuations under varying irradiance levels. These results highlight the ANN algorithm's effectiveness in optimizing power output in dynamic environments.

IV-7- Conclusion:

This research compares the performance of four Maximum Power Point Tracking (MPPT) algorithms: Artificial Neural Network (ANN), Fuzzy Logic Controller (FLC), Incremental Conductance (INC), and Perturb and Observe (P&O) under both constant and variable irradiation conditions. The results indicate that ANN consistently achieves the highest efficiency, reaching 96.63% under constant irradiation and 95.06% under variable conditions, due to its superior adaptability and predictive capabilities. INC serves as a reliable second-best option, offering strong performance (95.58% steady-state and 88.04% transient) with moderate computational complexity, while FLC and P&O fall below optimal levels in dynamic scenarios, with P&O suffering significant losses from steady-state oscillations and slower response times. Although FLC outperforms P&O during illumination changes, it remains less stable and efficient than ANN and INC; consequently, while ANN is ideal for maximizing efficiency in volatile environments, P&O and INC are better suited for cost-sensitive or simpler systems, providing a clear framework for selecting an algorithm based on specific environmental.

General Conclusion

General Conclusion

This study began by laying the foundation for understanding solar radiation and photovoltaic energy conversion principles, elucidating the mechanisms by which solar cells harness the photovoltaic effect to generate electricity. It explored the modeling, fundamental characteristics, and various environmental factors influencing the efficiency of photovoltaic generators, while also presenting the distinct classifications of photovoltaic cell types based on their specific silicon crystal structures. Building upon this, the crucial role of DC-DC converters in power management systems was explored. These converters facilitate efficient voltage conversion through various topologies like buck, boost, and buck-boost, enabling their widespread use across diverse industries.

The concept of Maximum Power Point Tracking (MPPT) was then introduced as a vital technology, particularly for renewable energy systems such as solar power installations. MPPT algorithms optimize energy extraction by continually adjusting the electrical operating point to track the maximum power output of photovoltaic panels.

This research led to an in-depth examination of MPPT principles, classifications, and implementation methods, focusing on a comparative evaluation of the Artificial Neural Network (ANN), Fuzzy Logic Controller (FLC), Incremental Conductance (INC), and Perturb and Observe (P&O) algorithms. Among the evaluated techniques, the ANN-based approach emerged as the most effective and reliable solution, its superior adaptability and predictive capabilities under both steady state and dynamic irradiance conditions make it the optimal method for maximizing energy extraction. While the FLC demonstrates high-performance tracking by effectively managing system non linearities, and the INC provides a robust alternative to the conventional P&O method, they both lack the advanced optimization precision inherent in the ANN architecture. Consequently, while traditional and fuzzy logic schemes remain viable for less complex or cost sensitive applications, the ANN algorithm stands out as the premier solution for ensuring robust performance and long term operational reliability in modern photovoltaic systems.

Bibliographical references

- [1] T. Li, A. Li, and Y. Song, "Development and utilization of renewable energy based on carbon emission reduction—evaluation of multiple MCDM methods," *Sustainability*, vol. 13, no. 17, p. 9822, 2021.
- [2] M. K. G. Deshmukh, M. Sameeroddin, D. Abdul, and M. A. Sattar, "Renewable energy in the 21st century: A review," *Materials Today: Proceedings*, vol. 80, pp. 1756-1759, 2023.
- [3] S. C. Aykut and A. Dahan, *Gouverner le climat?. Vingt ans de négociations internationales*. Sciences Po (Les Presses de), 2014.
- [4] N. Tekbıyık Ersoy, "Technology Based Renewable Energy Policy Analysis," in *Energy Efficiency and Renewable Energy Policies*: Springer, 2024, pp. 99-102.
- [5] M. Taylor, "Renewable Power Generation Cost Trends to 2022-Michael Taylor," 2023.
- [6] Y. P. Siwakoti, F. Z. Peng, F. Blaabjerg, P. C. Loh, and G. E. Town, "Impedance-source networks for electric power conversion part I: A topological review," *IEEE Transactions on power electronics*, vol. 30, no. 2, pp. 699-716, 2014.
- [7] J. Yuan, F. Blaabjerg, Y. Yang, A. Sangwongwanich, and Y. Shen, "An overview of photovoltaic microinverters: Topology, efficiency, and reliability," in *2019 IEEE 13th International Conference on Compatibility, Power Electronics and Power Engineering (CPE-POWERENG)*, 2019: IEEE, pp. 1-6.
- [8] Y. Liu, H. Abu-Rub, B. Ge, F. Blaabjerg, O. Ellabban, and P. C. Loh, "Applications in Photovoltaic Power Systems," 2016.
- [9] R. Panigrahi, S. K. Mishra, S. C. Srivastava, A. K. Srivastava, and N. N. Schulz, "Grid integration of small-scale photovoltaic systems in secondary distribution network—A review," *IEEE Transactions on Industry Applications*, vol. 56, no. 3, pp. 3178-3195, 2020.
- [10] Z. Tang, Y. Yang, and F. Blaabjerg, "Power electronics: The enabling technology for renewable energy integration," *CSEE Journal of Power and Energy Systems*, vol. 8, no. 1, pp. 39-52, 2021.
- [11] M. Islam, S. Mekhilef, and M. Hasan, "Single phase transformerless inverter topologies for grid-tied photovoltaic system: A review," *Renewable and sustainable energy reviews*, vol. 45, pp. 69-86, 2015.
- [12] D. Meneses, F. Blaabjerg, O. Garcia, and J. A. Cobos, "Review and comparison of step-up transformerless topologies for photovoltaic AC-module application," *IEEE Transactions on Power Electronics*, vol. 28, no. 6, pp. 2649-2663, 2012.

- [13] M. T. Outeiro, R. Visintini, and G. Buja, "Considerations in designing power supplies for particle accelerators," in *IECON 2013-39th Annual Conference of the IEEE Industrial Electronics Society*, 2013: IEEE, pp. 7076-7081.
- [14] M. T. Outeiro, G. Buja, and A. Carvalho, "Resonant converters for electric equipment power supply," in *IECON 2014-40th Annual Conference of the IEEE Industrial Electronics Society*, 2014: IEEE, pp. 5065-5071.
- [15] A. Richelli, M. Salem, and L. Colalongo, "A review of fully integrated and embedded power converters for IoT," *Energies*, vol. 14, no. 17, p. 5419, 2021.
- [16] M. Monsalve-Rueda, J. E. Candelo-Becerra, and F. E. Hoyos, "Dynamic behavior of a sliding-mode control based on a washout filter with constant impedance and nonlinear constant power loads," *Applied Sciences*, vol. 9, no. 21, p. 4548, 2019.
- [17] A. I. M. Ali, M. A. Sayed, and T. Takeshita, "Isolated single-phase single-stage DC-AC cascaded transformer-based multilevel inverter for stand-alone and grid-tied applications," *International Journal of Electrical Power & Energy Systems*, vol. 125, p. 106534, 2021.
- [18] A. Nabae, I. Takahashi, and H. Akagi, "A new neutral-point-clamped PWM inverter," *IEEE Transactions on industry applications*, no. 5, pp. 518-523, 1981.
- [19] B. Nour-Eddine, "Amélioration des performances de contrôle d'un système photovoltaïque par les méthodes métaheuristiques," El Oued, Université Echahid Hamma Lakhdar. Faculté des Sciences et Technologie, 2013.
- [20] S. Y. BOUDERHEM BRAHIM "Conception et Réalisation d'un Hacheur Boost MPPT à Base d'une Carte ARDUINO Application PV," 2017.
- [21] S. Dwari and L. Parsa, "An efficient high-step-up interleaved DC-DC converter with a common active clamp," *IEEE Transactions on Power Electronics*, vol. 26, no. 1, pp. 66-78, 2010.
- [22] F. L. Luo and H. Ye, *Advanced dc/dc converters*. crc Press, 2016.
- [23] A. S. Y. Alzahrani, *Advanced topologies of high-voltage-gain DC-DC boost converters for renewable energy applications*. Missouri University of Science and Technology, 2018.
- [24] R. P. Severns, G. Bloom, and R. P. Severns, *Modern DC-to-DC switchmode power converter circuits*. Springer, 1985.
- [25] S. Chakraborty, H.-N. Vu, M. M. Hasan, D.-D. Tran, M. E. Baghdadi, and O. Hegazy, "DC-DC converter topologies for electric vehicles, plug-in hybrid electric vehicles and fast charging stations: State of the art and future trends," *Energies*, vol. 12, no. 8, p. 1569, 2019.

- [26] https://www.toolify.ai/ai-news/complete-tutorial-implementing-ann-in-matlab-simulink-1764419#google_vignette (accessed).
- [27] M. D. S. M. C. Mr MEKKAOUI Saddam and AhmedYahia, "(Conception, simulation et réalisation d'un régulateur solaire avec commande MPPT à base d'une carte Arduino) ", UNIVERSITE EchahidHamma Lakhdar- EL Oued, 2022.
- [28] M. K. B. Abdelheq, "ETUDE ET REALISATION D'UN CONVERTISSEUR DC-DC," Université Aboubakr BelkaÛd-Tlemcen, 2018.
- [29] S. ABBOUDA, "« Contribution à la commande des systèmes photovoltaïques »,," Université de Reims Champagne-Ardenne et université de Sfax, 2015.
- [30] R. Touahir and M. B. Zahia, "contrôleur neuronal pour la poursuite du point de puissance maximale d'un système photovoltaïque," *Mémoire master, Université Kasdi Merbah, Ouargla, Algérie*, 2015.
- [31] S. H. E. Babaa, "High efficient interleaved boost converter with novel switch adaptive control in photovoltaic application," Newcastle University, 2013.
- [32] A. b. T. Bekhti Mohammed, "Maximum Power Point Tracking Simulations for PV Applications Using Matlab Simulink," *International Journal of Engineering Practical Research*, January 2014.
- [33] A. C. Pastor, "Conception et réalisation de modules photovoltaïques électroniques," INSA de Toulouse, 2006.
- [34] M. R. Patel, *Wind and solar power system*. CRC press, 1999.
- [35] R. Boukenoui, M. Ghanes, J.-P. Barbot, R. Bradai, A. Mellit, and H. Salhi, "Experimental assessment of Maximum Power Point Tracking methods for photovoltaic systems," *Energy*, vol. 132, pp. 324-340, 2017.
- [36] B. N. Alajmi, K. H. Ahmed, S. J. Finney, and B. W. Williams, "Fuzzy-logic-control approach of a modified hill-climbing method for maximum power point in microgrid standalone photovoltaic system," *IEEE transactions on power electronics*, vol. 26, no. 4, pp. 1022-1030, 2010.
- [37] A. A. Ghassami, S. M. Sadeghzadeh, and A. Soleimani, "A high performance maximum power point tracker for PV systems," *International Journal of Electrical Power & Energy Systems*, vol. 53, pp. 237-243, 2013.
- [38] G. Abdelmounaim, "An Advanced Neural Network-Based MPPT Controller for Photovoltaic Systems," University of El-Oued, 2023.
- [39] https://www.toolify.ai/ai-news/complete-tutorial-implementing-ann-in-matlab-simulink-1764419#google_vignette. (accessed).

Bibliographical references

- [40] <https://www.mathworks.com/help/deeplearning/ug/workflow-for-neural-network-design.html>. (accessed.

